SHARP SERVICE MANUAL

S42H1LC15C2EA

LCD COLOUR TELEVISION

MODEL LC-15C2EA

In the interests of user-safety (Required by safety regulations in some countries) the set should be restored to its original condition and only parts identical to those specified should be used.

CONTENTS

Page

- IMPORTANT SERVICE SAFETY PRECAUTION 2
- SPECIFICATIONS 3
- OPERATION MANUAL 4
- DIMENSIONS 5
- REMOVING OF MAJOR PARTS 6
- ADJUSTING PROCEDURE OF EACH SECTION 9
- TROUBLE SHOOTING TABLE 12
- CHASSIS LAYOUT 18
- BLOCK DIAGRAM 20
- OVERALL WIRING DIAGRAM 22
- DESCRIPTION OF SCHEMATIC DIAGRAM .. 24
- SCHEMATIC DIAGRAM
  - ■ OPERATION UNIT 25
  - ■ MAIN UNIT 26
  - ■ TUNER UNIT 38
  - ■ INVERTER UNIT 46
- PRINTED WIRING BOARD ASSEMBLIES 47
- PARTS LIST
  - ■ ELECTRICAL PARTS 51
  - ■ MAIN UNIT 51
  - ■ TUNER UNIT 55
  - ■ INVERTER UNIT 59
  - ■ OPERATION UNIT 59
  - ■ CABINET AND MECHANICAL PARTS 60
  - ■ ACCESSORIES PARTS 62
  - ■ PACKING PARTS 62
- PACKING OF THE SET 63

IMPORTANT SERVICE SAFETY PRECAUTION

■ **Service work should be perfomed only by qualified service technicians who are thoroughly familiar with all safety checks and the servicing guidelines which follow:**

WARNING

1. For continued safety, no modification of any circuit should be attempted.
2. Disconnect AC power before servicing.

CAUTION: FOR CONTINUED PROTECTION AGAINST A RISK OF FIRE REPLACE ONLY WITH SAME TYPE F1(1.25A, 250V), F2(1.25A, 250V), F6500 (1.25A, 250V) and F6501 (1.25A, 250V) FUSE.

BEFORE RETURNING THE RECEIVER (Fire & Shock Hazard)

Before returning the receiver to the user, perform the following safety checks:

1. Inspect all lead dress to make certain that leads are not pinched, and check that hardware is not lodged between the chassis and other metal parts in the receiver.
2. Inspect all protective devices such as non-metallic control knobs, insulation materials, cabinet backs, adjustment and compartment covers or shields, isolation resistor-capacitor networks, mechanical insulators and etc.
3. To be sure that no shock hazard exists, check for leakage current in the following manner.

- Plug the AC cord directly into a 110~240 volt AC outlet, and connect the DC power cable into the receiver's DC jack. (Do not use an isolation transformer for this test).
- Using two clip leads, connect a 50k ohm, 10 watt resistor paralleled by a 0.15µF capacitor in series with all exposed metal cabinet parts and a known earth ground, such as electrical conduit or electrical ground connected to an earth ground.
- Use an AC voltmeter having with 5000 ohm per volt, or higher, sensitivity or measure the AC voltage drop across the resisor.
- Connect the resistor connection to all exposed metal parts having a return to the chassis (antenna, metal cabinet, screw heads, knobs and control shafts, escutcheon, etc.) and measure the AC voltage drop across the resistor.
  All checks must be repeated with the AC cord plug connection reversed. (If necessary, a nonpolarized adaptor plug must be used only for the purpose of completing these checks.)
  Any reading of 0.75V peak (this corresponds to 0.5 milliamp. peak AC.) or more is excessive and indicates a potential shock hazard which must be corrected before returning the monitor to the owner.



SAFETY NOTICE

Many electrical and mechanical parts in LCD television have special safety-related characteristics.
These characteristics are often not evident from visual inspection, nor can protection afforded by them be necessarily increased by using replacement components rated for higher voltage, wattage, etc.
Replacement parts which have these special safety characteristics are identified in this manual; electrical components having such features are identified by " ⚠ " and shaded areas in the ***Replacement Parts Lists*** and ***Schematic Diagrams***.
For continued protection, replacement parts must be identical to those used in the original circuit.
The use of a substitute replacement parts which do not have the same safety characteristics as the factory recommended replacement parts shown in this service manual, may create shock, fire or other hazards.

Specifications

Items		15" LCD COLOUR TV, Model: LC-15C2EA
LCD panel		15" Advanced Super View & BLACK TFT LCD
Number of dots		921,600 dots
Video colour system		PAL/SECAM/NTSC
TV Function	TV-Standard (CCIR)	B/G, I, D/K, L
	TV-Tuning System	Auto preset 200 ch.
	STEREO/BILINGUAL	NICAM, IGR
	AUTO PRESET	Yes
	CATV	~Hyper Band
Brightness		430 cd/m^2
Lamp life		60,000 hours
Viewing angles		H: 170° V: 170°
Audio amplifier		2.1 W × 2
Speakers		5 cm ø 2 pcs.
Terminals	AV-IN 1	RGB
	AV-IN 2	S-VIDEO, VIDEO, AUDIO
	OUT	AUDIO
	Antenna	DIN
	Headphones	3.5 mm ø jack (Front)
OSD language		English/German/French/Spanish/Italian/Swedish/Dutch
Power requirement		DC 12 V, AC 110 V – 240 V, 50/60 Hz
Weight		5.3 kg, incl. stand, excl. accessories
Accessories		Operation manual, Remote Control, Batteries, AC adapter, AC cord, Cable clamps

Specifications are subject to change without prior notice.

Operation Manual

Controls

Front view



To change the vertical angle of the LCD TV set, tilt the screen up to 5 degrees forward or 10 degrees backward. The TV set can also be rotated 40 degrees horizontally. Please adjust the angle so that the TV set can be watched most comfortably.

Control panel


CH
TV/VIDEO
MENU
Headphones
MAIN POWER
Remote sensor window
(The actual location is not visible.)
Power/Standby indicator
A green indicator lights when the power is on and a red indicator lights when in the standby mode (the indicator will not light when the main power is off).
Volume (+)/(–)
Function same as ◀/▶ on the remote control when the menu is displayed.
MENU
TV/VIDEO
Functions same as OK on the remote control when the menu is displayed.
Remote sensor indicator
A red indicator blinks when the TV set receives the remote control signal.
CH (∧)/(∨)
Function same as ▲/▼ on the remote control when the menu is displayed.

Note:

- **TV/VIDEO**, **CH(∧)/(∨)**, and **Volume (+)/(–)** on the main unit have the same functions as the same buttons on the remote control. Fundamentally, this operation manual provides a description based on operation using the remote control.

Terminals



Rear view



Remote control



Dimensions



Unit: mm

REMOVING OF MAJOR PARTS

1. Remove the back cover.
2. Remove the table stand fixing screws (4 pcs.).
3. Remove the rear cabinet fixing screws (8 pcs.).
4. Front cabinet is opend in order of (4-1) to (4-9) , and detach the rear cabinet.
5. Peel off the tape.
6. Detach the connector from each PWB.





7. Remove the MAIN PWB fixing screws (4 pcs.).
8. Remove the INVERTER PWB fixing screws (2 pcs.).
9. Remove the 21-pin terminal fixing screw (2 pcs.).
10. Detach the chassis frame cover.
11. Remove the TUNER PWB fixing screws (5 pcs.).
12. Remove the OPERATION PWB fixing screws (2 pcs.).
13. Remove the chassis frame fixing screws (2 pcs.).
14. Remove the LCD panel ass'y fixing screws (2pcs).



- Precautions in handling the LCD panels
  1. Work in a clean room (with humidities below 50%).
  2. Be sure to wear an anti-static armband.
  3. Handle the panels on an electroconductive mat.
  4. Be careful not to fall, shake and shock the panels.

15. Remove the LCD display unit fixing screws (4 pcs.).
16. Detach the two diffusion sheets, reflection/deflection sheet and reflection sheet (cover).
17. Detach the four reflection mirrors.
18. Remove the fluorescent lamp.
19. Detach the lamp guide plate.
20. Detach the two lamp reflection sheets.



ADJUSTING PROCEDURE OF EACH SECTION

The best adjustment is made before shipping. If any position deviation is found or after part replace is performed, adjust as follows.

Preparation for adjustments

Use the dedicated AC adaptor or stable DC power supply.
LC15C2EA AC adaptor: UADP-0240CEZZ
DC power supply: 12V 4.0A

1. Adjusting procedure

- Checker adjustment
  Power ON (Adjustment processing mode) → Counter bias adjustment → TAMP (Contrast) adjustment → White balance adjustment

2. Entering the adjustment processing mode

There are the following two methods.

- Setting the pin (81)(KEY4) or pin (82)(KEY5) of IC2001 (microprocessor) to GND, turn on the power.
- A “POWER” key is made on with pushing an “TV/VIDEO” and “MENU” keys at the same time.(K of the inspection process mode is displayed by the upper left of the image plane.) → Next, “CH (∨)” and “VOL (–)” keys are pushed at the same time.(It becomes the image plane of the adjustment process mode.).....When it is canceled, it is made to turn it off.(Even off in the “MAIN POWER” key, off with R/C are good.)

3. Key operation in the adjustment process mode

- The receiving channel UP/DOWN is performed with the “CH (∧)/(∨)” keys.
  One push ... The UP/DOWN tuning is performed per channel.
  Continuous push ... The UP/DOWN search is performed until a next receivable station is found.
- Various adjustments
  The adjustment is performed for each item by the “MENU”, “Menu cursor”, “CH (∧)/(∨)” or “VOL (+)/(–)” keys (LCD TV set and remote control).
- Adjustment item is chosen with the Menu cursor upward/downward keys.
- The adjustment item makes a toggle operation with the “MENU” key input. (Next item)
  If the “MENU” key is input while the bottom item is selected, it moves to the top item on the next page.
- Press the auto preset button on the remote controller in the adjustment process mode, and the top item of the next page will show up regardless of which item appears now.
  Page 1 → Page 2 → ... → Page 23 → Page 1
- Press the manual memory button on the remote controller in the adjustment process mode, and the top item of the same page will show up.
- UP/DOWN of each adjustment vale selected is performed with the VOL (+)/(–) keys input.
- For P16 – 17, the unit enters the register select mode with the VOL (+)/(–) keys input while NTSC/PAL is selected, and the cursor moves to the address 01.
- The cursor moves up or down with the “CH (∧)/(∨)” keys and moves left or right with the VOL (+)/(–) keys, and a decision is made with the 12 key.
  When the decision is made, the cursor moves to the adjustment value selected, and UP/DOWN of each adjustment value selected by the “VOL (+)/(–)” keys input is performed.
  0 ↔ 1 ↔ ... ↔ 9 ↔ A ↔ ... ↔ F ↔ 0 ↔ ...
  Decide with the 12 key and return to the address select. Move to the next item with the “MENU” key.
  During address select, the cursor movement by the “VOL (+)/(–)” keys input is as follows:
  Example: 01 ↔ 02 ↔ 03 ↔ 01 ↔ ...
  The cursor movement by the “CH (∧)/(∨)” keys input is as follows:
  Example: 02 ↔ 05 ↔ ... ↔ F6 ↔ 02 ↔ ...

4. Initialization

When the microprocessor (IC2001) or the EEPROM (IC2004) has been replaced or when the EEPROM has been initialized, readjust the each adjustments.

4-1. Connect the pins (81) and (82) of IC2001 (microprocessor) to GND, and turn on the power.

4-2. Select the model name to (C2EA).

4-3. Select the inch size (15).

4-4. LED changes green from red after setting finish and about 15 seconds, initialization is completed, and it becomes adjustment mode.

5. Adjustment

5-1. +B adjustment...Page 1 +B-ADJ

Adjust the voltage of the pin (13) of P2002 to 5.00 ±0.02V.

Note: Since 5.0V is a reference voltage of all power voltage, adjust it precisely.

5-2. Counter-bias adjustment

Vary the "COM BIAS" setting on Page 2 of the adjustment process mode so that the contrast be sharpest (black looks most sinking).

5-3. TAMP adjustment

1) Receive the upper left of 75% white half colour bar signal.
2) See if the “Y” reading on page 2 of the adjusment process mode is somewhere following. If not, make the “PAL TAMP” adjustment to get the “Y” reading in the range of BF thru C9.
3) If the adjustment of “PAL TAMP” is executed, write its adjustment value to the “SECAM TAMP” manually.

(Screen of the page 2 of the adjustment processing menu OSD)

	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26
0		2																									
1		▶	C	O	M		B	I	A	S														1	2	0	
2			P	A	L		T	A	M	P															2	7	
3			S	E	C	A	M		T	A	M	P													2	7	
4			R	C	U	T	O	F	F																—	5	
5			G	C	U	T	O	F	F																	0	
6			B	C	U	T	O	F	F																—	1	
7			G	3			B	3			R	3					0	0			0	0			0	0	
8			G	1			B	4				Y					0	0			0	0			B	E	
9			T	A	M	P		H																	C	9	
10			T	A	M	P		L																	B	F	
11																											
12																											
13																											

Y Data
(White 75%)

5-4. White balance adjustment

Adjust “RCUTOFF” and “BCUTOFF” on the page 2 of the adjustment processing so as to obtain the colour of the same level as the standard set.

Note: For the adjustment processing of “RCUTOFF” and “BCUTOFF”, adjust them in the indication value range of ... –9, –7, ... –1, +1, ... +7, +9.

When it becomes even-numbered value, side favor noise sometimes occurs in the monochrome signal of the specific gradation.

6. Factory Setting

6-1. Perform a factory setting after completing all adjustments.
6-2. A “POWER” keys is made on with pushing an “TV/VIDEO” and “MENU” keys at the same time.
6-3. “K” of the inspection process mode is displayed on the screen upper left.
6-4. CH (∧) and VOL (+) keys are pushed about 2 seconds at the same time.
6-5. Release keys, if “E” is displayed on the screen upper left and “COMPLETE” is displayed on the bottom of it.
6-6. After a while, a power will be in a standby mode and a setup will be finished.
Note: “First installation” serves on “Deutsch”.

7. Lamp error detection

7-1. Functional description

This LCD colour television has a function (lamp error detection) to be turned OFF automatically for safety when the lamp or lamp circuit is abnormal.
If the lamp or lamp circuit is abnormal, or some other errors happen, and the lamp error detection is executed, the followings occur.

① The main unit of television is turned OFF 5 seconds after it is turned ON. (The power LED on the front side of TV turns from green to red.)
② If the situation ① happens 5 times sequentially, television can not be turned ON. (The power LED remains red.)

7-2. Countermeasures

7-2-1. Check when turning OFF the lamp error detection

When television is turned OFF by the lamp error detection mentioned above, it enters the adjustment process with the power LED red. Entering the adjustment process turns OFF the error detection and turns ON TV.
This enables the operation check to detect errors in the lamp or lamp circuit.
Check whether "ERROR NO RESET" on line 7, page 1 of the adjustment process is 1 or more. If it is 1 or more, it indicates the lamp error detection was executed.

7-2-2. Resetting of the lamp error count

After confirming that the lamp or lamp circuit is normal, reset the lamp error count. Select "ERROR NO RESET" on line 5, page 1 of the adjustment process and set the number to 0 using the volume button.

Page 1 of the adjustment process



Afterwards, perform the operation check to confirm that the lamp error detection does not function.

TROUBLE SHOOTING TABLE


No picture, No sound
Check all the settings microprocessor's adjust process menu.
Do F1 and F2 function?
No
Remove F1 and F2 and check the load side. Is there short-circuiting?
No
Replace F1 and F2.
Yes
Are T3701's secondary outputs +31V, +22V, +9V, +5V and -8V normal?
No
Is there short-circuiting of T3701 primary side periphery, Q3700, Q3701 and S4701?
No
Check S4701 and connection cable.
Yes
Is T3701's primary oscillator waveform normal?
No
Check J3702 periphery and connection cable.
Yes
Check T3701's secondary load.
Back light lamp failure to light up
Replace F6500 and F6501.
Yes
Is the pin (34) of IC1201 in the "H" state?
No
Check the OFL1 line, IC1201 and their peripheral parts.
Yes
Is the primary side of T6500~T6503 periphery short-circuiting?
No
Check T6500~T6503, Q6500~Q6505 and connection cable.
Yes
Replace the back light lamp with new one and check again.

TROUBLE SHOOTING TABLE (Continued)


No picture (1)
No picture at all
Check all the settings microprocessor's adjust process menu.
Is in/output of IC801 normal?
No
Check IC801 and its peripheral parts.
Yes
Is in/output of IC1201 normal?
No
Check IC1201 and its peripheral parts.
Yes
Check LCD panel voltages and waveform.
No TV and S-Video output
Is in/output of IC402 normal?
No
Check IC402 and its peripheral parts.
Yes
Is input at pin (73) of IC801 normal?
No
Check IC801, AV1 line and its peripheral parts.
No TV output
Is voltages at pins (6), (7) and (18) tuner normal?
No
Check the power line.
Yes
Is output at pin (13) of tuner normal?
No
Check tuner and its peripheral parts.
Yes
Is input at pin (3) of IC402 normal?
No
Check the its line.
Yes
Is the pins (2) and (4) of IC402 at "H" and "L" state?
No
Check IC402 and its peripheral parts.
Yes
Is the pins (65) and (66) of IC2001 at "H" and "L" state?
No
Check the its line.
No VIDEO 2 output
Is input at pin (75) of IC801 normal?
No
Check V1 IN line and its peripheral parts.

TROUBLE SHOOTING TABLE (Continued)


No picture (2)
No VIDEO 1 output
No S-VIDEO output
No TELETEXT output
Check all the settings microprocessor's adjust process menu.
Is input at pin (74) of IC801 normal?
No
Check the AV2 line and its peripheral parts.
Is input at pin (1) of IC402 and pin (71) of IC801 normal?
No
Check the W9, SY-line, SC-line and their peripheral parts.
Is input at pins (2), (5), (11), and (14) of IC1203 normal?
Yes
Check IC1203 and its peripheral parts.
No
Is input at pins (3), (4) and (5) of SC1602 normal?
Yes
Check connection cable
No
Is output at pins (1) and (7) of IC1619 and pin (1) of IC1620 normal?
No
Check IC1619, IC1620 and their peripheral parts.
Yes
Is output at pins (57)~(59) of IC1601 normal?
Yes
Check the R, G and B line.
No
Is input at pin (21) of IC1601 normal?
No
Check V2V0 line and its peripheral parts.
Yes
Check IC1601 and its peripheral parts.

TROUBLE SHOOTING TABLE (Continued)


No picture (3)
Colour is unusual
No picture image inversion
Gradation defect
Check all the settings microprocessor's adjust process menu.
Is output of R0~R7 normal?
No
Check R1202 and its peripheral parts.
Yes
Is output of G0~G7 normal?
No
Check R1203 and its peripheral parts.
Yes
Is output of B0~B7 normal?
No
Check R1204 and its peripheral parts.
Is in/output of SPIO and SPOI normal?
No
Check R1209 and its peripheral parts.
Yes
Is output of U/D normal?
No
Check IC1206, IC1207, Q1201 and their peripheral
Is output V0, V7, V17, V21, V32, V64, V112, V176, V235 and V255 normal?
No
Check IC1106, IC1107, IC1108, IC1114, IC1115 and their peripheral parts.

TROUBLE SHOOTING TABLE (Continued)


No sound (1)
No sound from front speakers
No sound from headphone
No sound from output line
TV sound failure
Check all the settins microprocessor's adjust process menu.
Is the pin (53) of IC2001 in the "L" state?
No
Muting effect is on. Check the FSMUTE line.
Yes
Is output at pins (27) and (28) of IC1901 normal?
No
Check IC1901 and its peripheral parts.
Yes
Is output at pins (1) and (7) of IC1903 normal?
No
Check IC1903 and its peripheral parts.
Yes
Is output at pins (8) and (12) of IC3305 normal?
No
Check IC3305 and its peripheral parts.
Yes
Check front speaker and connection cable.
Is the pin (52) of IC2001 in the "L" state?
No
Muting effect is on. Check the HP_MUTE line.
Yes
Is output at pins (24) and (25) of IC1901 normal?
No
Check IC1901 and its peripheral parts.
Yes
Is output at pins (1) and (7) of IC304 normal?
No
Check IC304 and its peripheral parts.
Yes
Check J5003 (Headphone Jack) and connection cable.
Is output at pins (33) and (34) of IC1901 normal?
No
Check IC1901 and its peripheral parts.
Yes
Is output at pins (1) and (7) of IC3500 normal?
No
Check IC3500 and its peripheral parts.
Is output at pin (11) of TU1 (Tuner) normal?
No
Check the tuner and its peripheral parts.
Yes
Is input at pins (67) and (69) of IC1901.
No
Check IC1901 and its peripheral parts.

TROUBLE SHOOTING TABLE (Continued)


No sound (2)
No sound from SCART
SCART sound failure
Check all the settings microprocessor's adjust process menu.
Is output at pins (36) and (37) of IC1901 normal?
No
Check IC1901 and its peripheral parts.
Yes
Is output at pins (1) and (7) of IC1902 normal?
No
Check IC1902 and its peripheral parts.
Is input at pins (53) and (54) of IC1901 normal?
No
Check their lines and their peripheral parts.
Yes
Is output at pins (27) and (28) of IC1901 normal?
No
Check IC1901 and its peripheral parts.

CHASSIS LAYOUT

MAIN PWB



INVERTER PWB



TUNER PWB



OPERATION PWB



BLOCK DIAGRAM



OVERALL WIRING DIAGRAM



DESCRIPTION OF SCHEMATIC DIAGRAM

VOLTAGE MEASUREMENT CONDITION:

1. Voltages at test points are measured at the supply voltage of AC 120V. Signals are fed by a color bar signal generator for servicing purpose and the above voltages are measured with a 20k ohm/V tester.

WAVEFORM MEASUREMENT CONDITION:

1. Waveforms at test points are observed at the supply voltage of AC 120V. Signals are fed by a color bar signal generator for servicing purpose.

INDICATION OF RESISTOR & CAPACITOR:

RESISTOR

1. The unit of resistance "Ω" is omitted. (K=kΩ=1000 Ω, M=MΩ).
2. All resistors are ± 5%, unless otherwise noted. (J= ± 5%, F= ± 1%, D= ± 0.5%)
3. All resistors are 1/10W, unless otherwise noted.
4. All resistors are Carbon type, unless otherwise noted.

Ⓒ: Solid Ⓦ: Cement
Ⓢ: Oxide Film Ⓣ: Special
Ⓝ: Metal Coating

CAPACITOR

1. All capacitors are μF, unless otherwise noted. (P=pF=μμF).
2. All capacitors are 50V, unless otherwise noted.
3. All capacitors are Ceramic type, unless otherwise noted.

(ML): Mylar (TA): Tantalum
(PF): Polypro Film (ST): Styrol

CAUTION:
This circuit diagram is original one, therefore there may be a slight difference from yours.

SAFETY NOTES:

1. ***DISCONNECT THE AC PLUG FROM THE AC OUTLET BEFORE REPLACEING PARTS.***
2. ***SEMICONDUCTOR HEAT SINKS SHOULD BE REGARDED AS POTENTIAL SHOCK HAZARDS WHEN THE CHASSIS IS OPERATING.***

IMPORTANT SAFETY NOTICE:

PARTS MARKED WITH "⚠" ( ) ARE IMPORTANT FOR MAINTAINING THE SAFETY OF THE SET. BE SURE TO REPLACE THESE PARTS WITH SPECIFIED ONES FOR MAINTAINING THE SAFETY AND PERFORMANCE OF THE SET.

SCHEMATIC DIAGRAM

■ OPERATION Unit



■ MAIN Unit-1/6


MAIN1
TO TUNER1 MA
SC2001 N0464FJ
L.ERR 50
GND 49
OFL 48
GND 47
TV_V 46 (TV_V)
GND 45
V2_V 44 (V2_V)
GND 43
V2VO 42
GND 41
EXT 40
SRESET 39 (SRESET)
SMUTE 38 (SMUTE)
L/R 37 (L/R)
SSTBY 36 (SSTBY)
HR 35
GND 34
HL 33
GND 32
LMUTE 31
SSYSTEM 30
R_ST 29 (R_ST)
GND 28
G_ST 27 (G_ST)
GND 26
B_ST 25 (B_ST)
GND 24
FSW1 23 (FSW1)
I2C/UA 22
GND 21
VI.IN 20 (VI.IN)
GND 19
VI.SY 18 (VI.SY)
GND 17
VI.SC 16 (VI.SC)
GND 15
S.SW 14
SLI 13
HP_MUTE 12
GND 11
SDAI 10 (SDAI)
GND 9
SCLI 8 (SCLI)
GND 7
MODE1 6
MODE2 5
AFT 4
GND 3
AGC 2
GND 1
TO TUNER4 MT
SC2002 N0487FJ
TEXT.BLK 20 (TEXT.BLK)
GND 19
TEXT.R 18 (TEXT.R)
TEXT.G 17 (TEXT.G)
TEXT.B 16 (TEXT.B)
GND 15
VS_HD 14 (VS_HD)
VS_VD 13 (VS_VD)
GND 12
STD 11
UPD 10 (UPD_N)
UPT 9 (UPT_N)
SUBCLK 8 (SUBCLK)
MRDY 7
GND 6
RESET1 5 (RESET1)
TXD 4 (TXD)
GND 3
RXD 2 (RXD)
GND 1
TO SW MS
P2003 N1258RE
HR 12
HL 11
GND 10
KEY2 9 (KEY2)
KEY1 8 (KEY1)
POW1 7
POW2 6
RC_IND 5
GND 4
POW 3
B5Vo 2
IREM 1
DUNTKB148DE
(QPWBXB148WJ)
TO MAIN6
B5VA
POW
S10.VCC
TO MAIN2
B5VA
B5V500MA
B3.3V200MA
CSYNC
V2VO
TV/AV
AV/IR
DDCRESET
TV_V
V2_V
R_ST
G_ST
B_ST
VI.IN
VI.SY
VI.SC
FSW1
SCL1
SDA1
TEXT.BLK
TEXT.R
TEXT.G
TEXT.B
TO MAIN4
OFL
VSH_IN
VSH_OUT
B3.3V200MA
OSDHD
OSDVD
OSD.SW
OSDR
OSDCK
OSDBLK
OSDB
OSDG
MPCLK
MPDA
MPCS
MPRDA
MPRCS
B5V500MA
S10.VCC
TO MAIN5
B5V500MA
DAC2CS
DAC1CS
MPDA
MPCLK
P2002
N1320RE
MC
1 IREM OUT
2 DAC1CS
3 MPCLK
4 MPDA
5 MPCS
6 MPRDA
7 MPRCS
8 SCL1
9 SDA1
10 GND
11 MRDY
12 IREM
13 B5V500MA
IC2001
IXA160WJ
IC2002
PST529DM
IC2004
BR2416E2
IC2030
M95640MN
IC2031
SN1G32C
IC2032
TC4W66F
IC751
AN7L05M +5V REG
IC752
BA033FP +3.3V REG
Q753 A1530AR
Q751 A1530AR
Q752 C144EE
Q2004 C144EE
Q2005 A144EE
Q2006 C144EE
D2002 EX0849CE 4.7V
D2001 DAN222
TP2001
TP2002
TP2005
TP2006 (KEY1)
TP2007 (KEY2)
TP2009
X2002 ZO169TA
(B3.3V200MA)
(B5VA)
(B5V500MA)
(V2VO)
(OSDVD)
(OSDHD)
(SRESET)
(L/R)
(SSTBY)
(UPD_N)
(UPT_N)
(SMUTE)
(SCL1)
(SDA1)
(SUBCLK)
(TXD)
(RXD)
(RESET1)
(CSYNC)
(IREM)
(MRDY)
(OSDCK)
(OSDBLK)

■ MAIN Unit-2/6


MAIN2
IC801
VPC3230D
IC401
BA7046F
IC402
NJM2235M
Q401
C3928AR
Q420
A1530AR
Q421
A1530AR
Q820
A1530AR
FL401
CA002WJ
FL801
CA002WJ
X801
20.25MHz
C0012CE
L804
C0055CE
L805
C0055CE
TP801
TP802
TO MAIN1
TO MAIN2
TO MAIN3
TO MAIN4
TO MAIN5
TO MAIN6
DUNTKB148DE
(QPWBXB148WJ)
(D+3.3V)
(B3.3V200MA)
(B5V500MA)
(FSW1)
(R_ST)
(G_ST)
(B_ST)
3.22.9

■ MAIN Unit-3/6


MAIN3
DUNTKB148DE
(QPWBXB148WJ)
TO MAIN2
RESET
VP_Y7
VP_Y6
VP_Y5
VP_Y4
VP_Y3
VP_Y2
VP_Y1
VP_Y0
LLC1
UV7
UV6
UV5
UV4
UV3
UV2
UV1
UV0
VSY
HSY
VACT1
R7020 0
R7021 0
R7024 0
R7003 0
R7018 0
R7022 0
R7023 0
TO MAIN4
B3.3V200MA
RESET
NR_Y7
NR_Y6
NR_Y5
NR_Y4
NR_Y3
NR_Y2
NR_Y1
NR_Y0
LLC1
NR_U7
NR_U6
NR_U5
NR_U4
NR_U3
NR_U2
NR_U1
NR_U0
RVS
RHS
VACT2

■ MAIN Unit-4/6


MAIN4
TO MAIN2
FIELD
HC
TEXT_BLK
TEXT_R
TEXT_G
TEXT_B
TO MAIN3
LLC1
RESET
RVS
RHS
VACT2
NR_U0
NR_U1
NR_U2
NR_U3
NR_U4
NR_U5
NR_U6
NR_U7
NR_Y0
NR_Y1
NR_Y2
NR_Y3
NR_Y4
NR_Y5
NR_Y6
NR_Y7
B3.3V200MA
TO MAIN1
MPCLK
MPDA
MPCS
MPRDA
MPRCS
OSDHD
OSDVD
OSDR
OSDG
OSDB
OSDBLK
OSDCK
OSD_SW
OFL
B3.3V200MA
B5V500MA
TO MAIN6
B29V10MA
TO MAIN5
B12V1A
B29V10MA2
REV
B-5.5V
CSCOM
V255
V235
V176
V112
V64
V32
V21
V17
V7
V0
B-15V
VGLCOM
VCOM
VPC3230D
IC1201
1X3378CE
LCD
CONTROLLER
PC
VPC3230D/PC
MICOM
OSD
FIFO
MEMORY
IC1206
LVX125FT
IC1207
TC4W66U
Q1201
C144EE
IC1202
PD485505
IC1203
1X1518CE
IC1208
PQ1R34++
Q1203
C144EE
Q1204
AI037KQ
Q1205
LMX2N++++
DUNTKB148DE
(QPWBXB148WJ)
LG
SC1203 N0206FJ
TO MAIN1
VSH_IN
VSH_OUT
S10.VCC
TO MAIN6
VSH3.3
SC1201 NA0206FJ
SC1202 NO4JEFJ

■ MAIN Unit-5/6


MAIN5
TO MAIN1
TO MAIN6
TO MAIN4
IC1101 MB8346BV
IC1102 NJM4565V
IC1103 NJM2060V
IC1104 NJM2060V
IC1105 BU4053V
IC1106 NJM4580V
IC1107 NJM4580V
IC1108 NJM4580V
IC1109 NJM353M
IC1110 BU4053V
IC1111 MB8346BV
IC1112 BU4053V
IC1113 BU4053V
IC1114 NJM4580V
IC1115 NJM4580V
IC1116 NJM2147M
Q1101 A1729
Q1102 C4520
Q1103 A1036K
Q1104 A1036K
Q1105 A1036K
Q1106 FMMT718
Q1107 C144EE
Q1108 C4520
Q1109 A1729
D1101 1SS250
D1107 1SS250
D1106 DAN222
D1108 DAN222
D1109 DAN222
D1110 DAN222
DUNTKB148DE
(QPWBXB148WJ)

■ MAIN Unit-6/6


MAIN6
DUNTKB148DE
(QPWBSB148WJ)
TO MAIN2
B9V200MA
B-8V1A
B12V1A
TO MAIN5
B12V1A
B5V500MA
B-8V1A
B-20V10MA
B9V200MA
+BADJ
TO MAIN4
VSH3.3
B29V10MA
TO MAIN1
POW
SIG.VCC
B5VA
P3702
N11780E
MB
TO TUNER2
1 SIG VCC
2 SIG VCC
3 B12V1A
4 B31V
5 B9V200MA
6 B8V
7 B5V500MA
8 BTU5V500MA
9 B5VA
10 GND
11 GND
(B5V500MA)
(B-20V10MA)
(B9V200MA)
Q3710 C144EE
D3711 DAN222
R3759 1K (1/4W)
Q3709 FMMT718
R3766 4.7K
C3740 0.1u 25V Z
R3701 1 (1/4W)
Q3700 FMMT718
R3700 4.7K
C3700 0.1u 25V Z
R3702 1K (1/4W)
D3700 DAN222
Q3701 C144EE
D3704 1SS250
C3714 47u 50V (ASH)
C3715 0.1u 50V (TV)
R3725 0
R3726 68K (1/8W)
FB3704 0051TA
FB3706 0254TA
D3706 SFPB74
C3718 330u 16V (ASH)
C3717 1u 16V (TV)
R3729 0
R3730 22K
C3720 180P (CH)
FB3707 0254TA
D3707 SFPB74
C3721 1u 16V (TV)
C3722 150u 6.3V (APF)
FB3708 0051TA
R3724 1
D3708 DAN222
C3724 330u 16V (ASH)
C3725 1u 16V (TV)
R3731 2.2K
R3732 0
FB3705 0051TA
D3705 1SS250
C3716 220u 25V (ASH)
C3719 0.1u 25V Z
R3727 0
R3728 39K
L3700 C0130CE
R3718 820 (1W)
C3712 82u 16V (APF)
C3711 5600P
D3703 SFPB56
FB3700 0095CE
C3713 5600P
R3722 0
T3701 W0010CE
FB3701 0095CE
R3721 0
Q3702 K2503
FB3709 0095CE
R3716 0 (1/2W)
C3701 4.7u 25V
R3703 270K
R3704 13K F
R3705 180K
R3706 10
C3702 1u 10V KZ1025CE
C3703 22u 16V (APT)
C3704 470P (CH)
REF CT CS V+
IN- F.B. GND OUT
IC3701 NJM2377M
R3707 1M
C3705 0.01u 25V
R3708 6.8K
R3710 12K F
R3711 1.5K F
R3709 2.7K F
R3712 68K F
R3713 56K F
D3701 DAN222
Q3703 C3928AR
R3714 47K
C3709 1u 16V (TV)
R3715 10K
L3702 C0130CE
C3727 470u 6.3V (APW)
C3728 1u 16V (TV)
Q3707 C3928AR
R3740 47K F
C3735 0.01u Z
R3739 6.2K F
R3738 10K F
R3737 10K
D3709 DAN222
R3752 1K
C3734 0.1u 25V Z
R3762 560 (1/4W)
Q3704 FMMT619
C3730 0.1u 50V (TV)
R3733 1K
IC3702 NJM2147M
C3741 2.2u 50V (APF)
R3741 11K F
R3736 22K F
R3735 12K F
R3734 10K F
R3742 1.8K F
R3743 1.2K F
R3745 6.8K F
R3746 1.2K F
R3749 1K
C3732 1u 10V KZ1025CE
C3733 1u 10V KZ1025CE
R3750 390
R3751 10K (1/10W)
Q3706 FMY3

■ TUNER Unit-1/4



■ TUNER Unit-2/4



■ TUNER Unit-3/4



■ TUNER Unit-4/4

TUNER 4



■ INVERTER Unit



PRINTED WIRING BOARD ASSEMBLIES



OPERATION Unit (Component Side)



INVERTER Unit (Component Side)

1	2	3	4	5	6



MAIN Unit (Side-A)



MAIN Unit (Side-B)


MT
MB
MA
SB152WJ
KB152DE
SR
SL
VE
VF
F1 T1.25A L 250V
F2 T1.25A L 250V
TU1
SC1602
P1903
P3704
P3601
P3602
P3603
P3604
J3903
J3902
J5003
J5001
J3702
SC5001
IC1605
IC1615
IC1614
IC1608
IC1603
IC1612
IC1602
IC1604
IC1620
IC1607
IC1611
IC1616
IC2200
IC3500
IC1903
IC3305
IC1304
IC344
Q3911
Q3910
Q1607
Q1606
Q1631
Q1632
Q1633
Q2202
Q2203
Q2204
Q3907
Q3306
Q3307
Q3304
D3905
D303
D5701
L3202
C2200
C1928
C1662
C1661
C1656
C1655
C1657
C1623
C2222
C339
C342
C3954
C3955
C3956
C3961
C3962
C3963
C1936
C1942
C3374
C3361
C3372
C3369
C3505
C3508
C3506
C1910
C1907
C1908
C1926
C1911
C1938
C1939
C1941
C1902
C1901
C2201
C2214
C2217
C2225
C3202
C3958
C3960
C3959
C3010
C3373
C3371
C3367
C3360
C3302
C3301
C3305
C3359
C3603
C3604
C3608
C3609
C3610
C3611
C3612
C3613
C3614
C3615
C3616
C3617
C3618
C3619
C3620
C3621
C3622
C3623
C3624
C3625
C3626
C3627
C3628
C3629
C3630
C3631
C3632
C3633
C3634
C3635
C3636
C3637
C3638
C3639
C3640
C3641
C3642
C3643
C3644
C3645
C3646
C3647

PARTS LIST

PARTS REPLACEMENT

Replacement parts which have these special safety characteristics identified in this manual; electrical components having such features are identified by ⚠ and shaded areas in the Replacement Parts Lists and Schematic Diagrams. The use of a substitute replacement part which does no have the same safety characteristic as the factory recommended replacement parts shown in this service manual may create shock, fire or other hazards.

"HOW TO ORDER REPLACEMENT PARTS"

To have your order filled promptly and correctly, please furnish the following informations.

1. MODEL NUMBER
2. REF. NO.
3. PART NO.
4. DESCRIPTION

★ MARK: SPARE PARTS-DELIVERY SECTION

Ref. No.	Part No.	★	Description	Code

PRINTED WIRING BOARD ASSEMBLIES
(NOT REPLACEMENT ITEM)

	DUNTKB148FE52	–	MAIN Unit	—
	DUNTKB149DE02	–	TUNER Unit	—
	DUNTKB150DE02	–	INVERTER Unit	—
	DUNTKB151DE02	–	OPERATION Unit	—

LCD PANEL

NOTE: THE PARTS HERE SHOWN ARE SUPPLIED AS AN ASSEMBLY BUT NOT INDEPENDENTLY.

	RLCDTA003WJZZ	J	15' LCD Panel Unit	DB

DUNTKB148FE52 MAIN UNIT

INTEGRATED CIRCUITS

IC401	VHiBA7046F/-1	J	BA7046F	AF
IC402	VHiNJM2235M-1	J	NJM2235M	AE
IC751	VHiAN77L05M-1	J	AN77L05M-E1	AG
IC752	VHiBA033FP/-1	J	BA033FP-E2	AG
IC801	VHiVPC3230D1EQ	J	VPC3230D-QA-B3	BD
IC1101	VHiMB8346BV-1	J	MB88346BPFV	AN
IC1102	VHiNJM4565V-1	J	NJM4565V	AF
IC1103	VHiNJM2060V-1	J	NJM2060V	AF
IC1104	VHiNJM2060V-1	J	NJM2060V	AF
IC1105	VHiBU4053V/-1	J	BU4053BCFV-E2	AE
IC1106	VHiNJM4580V-1	J	NJM4580V	AE
IC1107	VHiNJM4580V-1	J	NJM4580V	AE
IC1108	VHiNJM4580V-1	J	NJM4580V	AE
IC1109	VHiNJM353M/-1	J	NJM353M	AG
IC1110	VHiBU4053V/-1	J	BU4053BCFV-E2	AE
IC1111	VHiMB8346BV-1	J	MB88346BPFV	AN
IC1112	VHiBU4053V/-1	J	BU4053BCFV-E2	AE
IC1113	VHiBU4053V/-1	J	BU4053BCFV-E2	AE
IC1114	VHiNJM4580V-1	J	NJM4580V	AE
IC1115	VHiNJM4580V-1	J	NJM4580V	AE
IC1116	VHiNJM2147M-1	J	NJM2147M-TE1	AF
IC1201	RH-iX3378CEN1	J	LR38815	
IC1202	VHiPD485505-2	J	UPD485505G-25	AY
IC1203	RH-iX1518CEZZ	J	TC74HC157AF	AG
IC1206	VHiLVX125FT-1	J	TC74LVX125FT	AG
IC1207	VHiTC4W66U/-1	J	TC4W66FU	AF
IC1208	VHiPQ1R34++-1Y	J	PQ1R34	AE
IC2001	RH-iXA160WJZZQ	J	M306V0ME-161FP	BA
IC2002	VHiPST529DM-1	J	PST529DMT	AE
IC2004	VHiBR2416E2-1	J	BR24C16F	AK
IC2030	VHiM95640MN-1Y	J	I.C.	AK
IC2031	VHiSNT1G32C-1	J	SN74AHCT1G32DC	AD
IC2032	VHiTC4W66F/-1	J	TC4W66F	AE
IC3701	VHiNJM2377M-1	J	NJM2377M	AK
IC3702	VHiNJM2147M-1	J	NJM2147M-TE1	AF

TRANSISTORS

Q401	VS2SC3928AR-1	J	2SC3928AR	AB
Q420	VS2SA1530AR-1	J	2SA1530AR	AB
Q421	VS2SA1530AR-1	J	2SA1530AR	AB
Q751	VS2SA1530AR-1	J	2SA1530AR	AB
Q752	VSDTC144EE/-1	J	DTC144EE	AA
Q753	VS2SA1530AR-1	J	2SA1530AR	AB
Q820	VS2SA1530AR-1	J	2SA1530AR	AB
Q1101	VS2SA1729//-1	J	2SA1729	AF
Q1102	VS2SC4520//-1	J	2SC4520	AE
Q1103	VS2SA1036K/-1	J	2SA1036K	AC
Q1104	VS2SA1036K/-1	J	2SA1036K	AC
Q1105	VS2SA1036K/-1	J	2SA1036K	AC
Q1106	VSFMMT718//-1	J	FMMT718	AE
Q1107	VSDTC144EE/-1	J	DTC144EE	AA
Q1108	VS2SC4520//-1	J	2SC4520	AE
Q1109	VS2SA1729//-1	J	2SA1729	AF
Q1201	VSDTC144EE/-1	J	DTC144EE	AA
Q1203	VSDTC144EE/-1	J	DTC144EE	AA
Q1204	VS2SA1037KQ-1	J	2SA1037KQ	AA
Q1205	VSUMX2N++++-1Y	J	UMX2N++++	AB
Q2004	VSDTC144EE/-1	J	DTC144EE	AA
Q2005	VSDTA144EE/-1	J	DTA144EE	AA
Q2006	VSDTC144EE/-1	J	DTC144EE	AA
Q3700	VSFMMT718//-1	J	FMMT718	AE
Q3701	VSDTC144EE/-1	J	DTC144EE	AA
Q3702	VS2SK2503//-1	J	2SK2503	AE
Q3703	VS2SC3928AR-1	J	2SC3928AR	AB
Q3704	VSFMMT619//-1	J	FMMT619	AE
Q3706	VSFMY3/////-1	J	FMY3/////	AB
Q3707	VS2SC3928AR-1	J	2SC3928AR	AB
Q3709	VSFMMT718//-1	J	FMMT718	AE
Q3710	VSDTC144EE/-1	J	DTC144EE	AA

DIODES

D1101	VHD1SS250//1E	J	Diode	AB
D1106	VHDDAN222//-1	J	Diode	AA
D1107	VHD1SS250//1E	J	Diode	AB
D1108	VHDDAN222//-1	J	Diode	AA
D1109	VHDDAN222//-1	J	Diode	AA
D1110	VHDDAN222//-1	J	Diode	AA
D1201	VHD1SS250//1E	J	Diode	AB
D1203	VHDRB491D++-1Y	J	Diode	AD
D1205	VHDDAN222//-1	J	Diode	AA
D1206	RH-EX0227CEZZ	J	Zener Diode	AB
D1208	VHDDAN222//-1	J	Diode	AA
D1209	RH-EX1247CEZZY	J	Zener Diode	AB
D1210	VHDDAN222//-1	J	Diode	AA
D1211	VHDDAN222//-1	J	Diode	AA
D1212	VHDRB481K++-1Y	J	Diode	AD
D2001	VHDDAN222//-1	J	Diode	AA
D2002	RH-EX0849CEZZ	J	Zener Diode	AC
D3700	VHDDAN222//-1	J	Diode	AA
D3701	VHDDAN222//-1	J	Diode	AA
D3703	VHDSFPB56//2E	J	Diode	AC
D3704	VHD1SS250//1E	J	Diode	AB
D3705	VHD1SS250//1E	J	Diode	AB
D3706	VHDSFPB74//2E	J	Diode	AD
D3707	VHDSFPB74//2E	J	Diode	AD
D3708	VHDDAN222//-1	J	Diode	AA
D3709	VHDDAN222//-1	J	Diode	AA
D3711	VHDDAN222//-1	J	Diode	AA

DUNTKB148FE52
MAIN UNIT (Continued)

PACKAGED CIRCUITS

Ref. No.	Part No.	★	Description	Code
X801	RCRSC0012CEZZ	J	Crystal	AH
X2002	RFiLZ0169TAZZY	J	Filter	AD

FILTERS AND COILS

Ref. No.	Part No.	★	Description	Code
FL401	RFiLCA002WJZZY	J	Filter	AG
FL801	RFiLCA002WJZZY	J	Filter	AG
L804	RCiLC0055CEZZ	J	Coil	AD
L805	RCiLC0055CEZZ	J	Coil	AD
L1201	VP-1M470J5R4N	J	Peaking 47µH	AC
L1202	RCiLC0055CEZZ	J	Coil	AD
L1203	VP-1M220J2R9N	J	Peaking 22µH	AC
L1204	VP-1M220J2R9N	J	Peaking 22µH	AC
L1205	VP-1M220J2R9N	J	Peaking 22µH	AC
L3700	RCiLC0130CEZZ	J	Coil	AG
L3702	RCiLC0130CEZZ	J	Coil	AG

TRANSFORMER

Ref. No.	Part No.	★	Description	Code
T3701	RTRNW0010CEZZY	J	Transformer	AL

CAPACITORS

Ref. No.	Part No.	★				Code
C401	VCKYTV1AB105K	J	1	10V	Ceramic	AD
C402	VCKYCY1HB102K	J	1000p	50V	Ceramic	AA
C403	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C404	VCEAPF1AW476M	J	47	10V	Electrolytic	AB
C405	VCKYCY1HB222K	J	2200p	50V	Ceramic	AA
C406	VCKYTV1AB105K	J	1	10V	Ceramic	AD
C407	VCCCCY1HH101J	J	100p	50V	Ceramic	AA
C408	VCKYTV1AB105K	J	1	10V	Ceramic	AD
C409	VCKYTV1AB105K	J	1	10V	Ceramic	AD
C410	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C413	VCCCCY1HH331J	J	330p	50V	Ceramic	AA
C414	VCCCCY1HH151J	J	150p	50V	Ceramic	AA
C751	VCKYTV1CF105Z	J	1	16V	Ceramic	AB
C752	VCEAPF1CN226M	J	22	16V	Electrolytic	AD
C753	VCKYTV1CF105Z	J	1	16V	Ceramic	AB
C755	VCKYCY1CF334Z	J	0.33	16V	Ceramic	AA
C756	VCEAPF0JN226M	J	22	6.3V	Electrolytic	AD
C801	VCEAPF1CN106M	J	10	16V	Electrolytic	AD
C802	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C803	VCCCCY1HH7R0D	J	7p	50V	Ceramic	AA
C804	VCCCCY1HH7R0D	J	7p	50V	Ceramic	AA
C805	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C806	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C809	VCEAPK1CN107M	J	100	16V	Electrolytic	AD
C810	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C812	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C813	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C814	VCKYCY1HB102K	J	1000p	50V	Ceramic	AA
C815	VCKYTV1CF684Z	J	0.68	16V	Ceramic	AB
C816	VCKYTV1CF684Z	J	0.68	16V	Ceramic	AB
C817	VCKYTV1CF684Z	J	0.68	16V	Ceramic	AB
C818	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C819	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C820	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C821	VCEAPW1CN477M	J	470	16V	Electrolytic	AE
C822	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C823	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C826	VCEAPF0GW107M	J	100	4V	Electrolytic	AC
C827	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C830	VCKYCY1CF224Z	J	0.22	16V	Ceramic	AA
C831	VCKYCY1CF224Z	J	0.22	16V	Ceramic	AA
C832	VCKYCY1CF224Z	J	0.22	16V	Ceramic	AA
C833	VCEAPF0GW107M	J	100	4V	Electrolytic	AC
C834	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C835	VCEAPF0JW107M	J	100	6.3V	Electrolytic	AC
C836	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C837	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C838	VCEAPF0GW107M	J	100	4V	Electrolytic	AC
C839	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C840	VCKYTV1CF684Z	J	0.68	16V	Ceramic	AB
C842	VCKYCY1CF104Z	J	0.1	16V	Ceramic	AA
C843	VCCCCY1HH180J	J	18p	50V	Ceramic	AA
C844	VCCCCY1HH180J	J	18p	50V	Ceramic	AA
C845	VCCCCY1HH180J	J	18p	50V	Ceramic	AA
C846	VCCCCY1HH180J	J	18p	50V	Ceramic	AA
C847	VCCCCY1HH180J	J	18p	50V	Ceramic	AA
C848	VCCCCY1HH101J	J	100p	50V	Ceramic	AA
C850	VCCCCY1HH180J	J	18p	50V	Ceramic	AA
C1101	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1102	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1103	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1104	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1105	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1107	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1108	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1109	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1110	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1111	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1112	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1113	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1114	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1115	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1116	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1117	VCCCCY1HH560J	J	56p	50V	Ceramic	AA
C1118	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1119	VCKYTV1CF105Z	J	1	16V	Ceramic	AB
C1120	VCKYTV1EF104Z	J	0.1	25V	Ceramic	AB
C1122	VCKYTV1CF105Z	J	1	16V	Ceramic	AB
C1123	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1124	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1125	VCEASM1CN107MY	J	100	16V	Electrolytic	AD
C1126	RC-EZ1339CEZZ	J	220	16V	Electrolytic	AD
C1129	RC-EZ1339CEZZ	J	220	16V	Electrolytic	AD
C1130	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1131	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1132	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1133	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1134	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1135	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1136	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1137	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1138	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1139	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1141	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1142	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1143	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1144	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1145	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1146	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1147	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1148	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1149	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1150	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1151	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1152	VCCCCY1HH181J	J	180p	50V	Ceramic	AA
C1153	VCKYTV1HB103K	J	0.01	50V	Ceramic	AA
C1154	VCKYTV1HB103K	J	0.01	50V	Ceramic	AA
C1155	VCKYTV1CB334K	J	0.33	16V	Ceramic	AC
C1156	VCCCCY1HH560J	J	56p	50V	Ceramic	AA
C1157	VCKYTV1CB105K	J	1	16V	Ceramic	AC
C1203	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1204	VCCCCY1HH220J	J	22p	50V	Ceramic	AA
C1205	VCCCCY1HH220J	J	22p	50V	Ceramic	AA
C1206	VCEASM1HN106MY	J	10	50V	Electrolytic	AD
C1207	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1208	VCKYTV1HF104Z	J	0.1	50V	Ceramic	AA
C1209	VCEASH0JN227MY	J	220	6.3V	Electrolytic	AC
C1210	VCEASM0GW107MY	J	100	4V	Electrolytic	AC
C1211	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1212	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1213	VCEASM1CW107MY	J	100	16V	Electrolytic	AD
C1214	VCEASM0GW107MY	J	100	4V	Electrolytic	AC
C1215	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C1217	VCEASM1HN475MY	J	4.7	50V	Electrolytic	AD
C1218	VCEASM1CN106MY	J	10	16V	Electrolytic	AC
C1219	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1223	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA

DUNTKB148FE52
MAIN UNIT (Continued)

Ref. No.	Part No.	★			Description	Code
C1224	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1225	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1226	VCEASM1HN106MY	J	10	50V	Electrolytic	AD
C1227	VCKYTV1CB105K	J	1	16V	Ceramic	AC
C1228	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C1229	VCEASM1CN226MY	J	22	16V	Electrolytic	AD
C1230	VCKYTV1CB105K	J	1	16V	Ceramic	AC
C1231	VCEASM1CN107MY	J	100	16V	Electrolytic	AD
C1232	VCKYTV1HF104Z	J	0.1	50V	Ceramic	AA
C1240	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1241	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1242	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1243	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C2001	VCKYCY1HB102K	J	1000p	50V	Ceramic	AA
C2002	VCCCCY1HH221J	J	220p	50V	Ceramic	AA
C2003	VCEAPF1HW105M	J	1	50V	Electrolytic	AB
C2006	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C2007	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C2009	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C2010	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C2011	VCCCCY1HH220J	J	22p	50V	Ceramic	AA
C2016	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C2017	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C2030	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C2031	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C2100	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C3700	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C3701	VCEAPF1EW475M	J	4.7	25V	Electrolytic	AB
C3702	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C3703	VCEAPT1CN226M	J	22	16V	Electrolytic	AC
C3704	VCCCCY1HH471J	J	470p	50V	Ceramic	AA
C3705	VCKYCY1EB103K	J	0.01	25V	Ceramic	AA
C3709	VCKYTV1CF105Z	J	1	16V	Ceramic	AB
C3711	VCKYCY1HB562K	J	5600p	50V	Ceramic	AA
C3712	VCAAPF1CJ826MY	J	82	16V	Electrolytic	AG
C3713	VCKYCY1HB562K	J	5600p	50V	Ceramic	AA
C3714	VCEASH1HN476MY	J	47	50V	Electrolytic	AD
C3715	VCKYTV1HF104Z	J	0.1	50V	Ceramic	AA
C3716	VCEASH1EN227MY	J	220	25V	Electrolytic	AE
C3717	VCKYTV1CF105Z	J	1	16V	Ceramic	AB
C3718	VCEASH1CN337MY	J	330	16V	Electrolytic	AE
C3719	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C3720	VCCCCY1HH181J	J	180p	50V	Ceramic	AA
C3721	VCKYTV1CF105Z	J	1	16V	Ceramic	AB
C3722	VCAAPF0JJ157MY	J	150	6.3V	Electrolytic	AG
C3724	VCEASH1CN337MY	J	330	16V	Electrolytic	AE
C3725	VCKYTV1CF105Z	J	1	16V	Ceramic	AB
C3727	VCEAPW0JN477M	J	470	6.3V	Electrolytic	AE
C3728	VCKYTV1CF105Z	J	1	16V	Ceramic	AB
C3730	VCKYTV1HF104Z	J	0.1	50V	Ceramic	AA
C3732	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C3733	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C3734	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C3735	VCKYCY1HF103Z	J	0.01	50V	Ceramic	AA
C3740	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C3741	VCEAPF1HN225M	J	2.2	50V	Electrolytic	AD

RESISTORS

R401	VRS-CY1JF104J	J	100k	1/16W	Metal Oxide	AA
R402	VRS-CY1JF333J	J	33k	1/16W	Metal Oxide	AA
R403	VRS-CY1JF103J	J	10k	1/16W	Metal Oxide	AA
R404	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R405	VRS-CY1JF681J	J	680	1/16W	Metal Oxide	AA
R406	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R408	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R409	VRS-CY1JF103J	J	10k	1/16W	Metal Oxide	AA
R410	VRS-CY1JF474J	J	470k	1/16W	Metal Oxide	AA
R414	VRS-CY1JF105J	J	1M	1/16W	Metal Oxide	AA
R415	VRS-CY1JF105J	J	1M	1/16W	Metal Oxide	AA
R416	VRS-CY1JF105J	J	1M	1/16W	Metal Oxide	AA
R417	VRS-CY1JF331J	J	330	1/16W	Metal Oxide	AA
R418	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R419	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R420	VRS-CY1JF152J	J	1.5k	1/16W	Metal Oxide	AA
R421	VRS-CY1JF332J	J	3.3k	1/16W	Metal Oxide	AA
R422	VRS-CY1JF471J	J	470	1/16W	Metal Oxide	AA
R424	VRS-CY1JF331J	J	330	1/16W	Metal Oxide	AA
R427	VRS-CY1JF561J	J	560	1/16W	Metal Oxide	AA
R428	VRS-CY1JF561J	J	560	1/16W	Metal Oxide	AA
R430	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R726	VRS-CY1JF1R0J	J	1	1/16W	Metal Oxide	AA
R751	VRS-CY1JF1R0J	J	1	1/16W	Metal Oxide	AA
R752	VRS-CY1JF154J	J	150k	1/16W	Metal Oxide	AA
R753	VRS-CY1JF274J	J	270k	1/16W	Metal Oxide	AA
R775	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R777	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R789	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R790	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R801	VRS-CB1JF221J	J	220	1/16W	Metal Oxide	AC
R802	VRS-CB1JF220J	J	22	1/16W	Metal Oxide	AC
R803	VRS-CB1JF220J	J	22	1/16W	Metal Oxide	AC
R804	VRS-CA1JF101J	J	100	1/16W	Metal Oxide	AA
R805	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R810	VRS-CB1JF220J	J	22	1/16W	Metal Oxide	AC
R811	VRS-CY1JF222J	J	2.2k	1/16W	Metal Oxide	AA
R812	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R813	VRS-CB1JF220J	J	22	1/16W	Metal Oxide	AC
R814	VRS-CY1JF332J	J	3.3k	1/16W	Metal Oxide	AA
R815	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R816	VRS-CY1JF470J	J	47	1/16W	Metal Oxide	AA
R817	VRS-CY1JF332J	J	3.3k	1/16W	Metal Oxide	AA
R818	VRS-CY1JF331J	J	330	1/16W	Metal Oxide	AA
R819	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R820	VRS-CA1JF101J	J	100	1/16W	Metal Oxide	AA
R821	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R822	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R826	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R830	VRS-CY1JF561J	J	560	1/16W	Metal Oxide	AA
R832	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R836	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R838	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R840	VRS-CY1JF221J	J	220	1/16W	Metal Oxide	AA
R851	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R852	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R853	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R854	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1001	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R1002	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1003	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1005	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1006	VRS-CY1JF243F	J	24k	1/16W	Metal Oxide	AA
R1007	VRS-CY1JF563F	J	56k	1/16W	Metal Oxide	AA
R1008	VRS-CY1JF822F	J	8.2k	1/16W	Metal Oxide	AA
R1009	VRS-CY1JF682F	J	6.8k	1/16W	Metal Oxide	AA
R1013	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R1014	VRS-CY1JF103J	J	10k	1/16W	Metal Oxide	AA
R1016	VRS-CY1JF103J	J	10k	1/16W	Metal Oxide	AA
R1017	VRS-CY1JF272J	J	2.7k	1/16W	Metal Oxide	AA
R1019	VRS-CY1JF473J	J	47k	1/16W	Metal Oxide	AA
R1020	VRS-CY1JF472J	J	4.7k	1/16W	Metal Oxide	AA
R1021	VRS-TW2ED102J	J	1k	1/4W	Metal Oxide	AA
R1022	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1024	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1025	VRS-CY1JF123F	J	12k	1/16W	Metal Oxide	AA
R1026	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1027	VRS-CY1JF123F	J	12k	1/16W	Metal Oxide	AA
R1028	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1029	VRS-CY1JF123F	J	12k	1/16W	Metal Oxide	AA
R1030	VRS-TW2ED150J	J	15	1/4W	Metal Oxide	AB
R1031	VRS-CY1JF123F	J	12k	1/16W	Metal Oxide	AA
R1032	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1033	VRS-CY1JF123F	J	12k	1/16W	Metal Oxide	AA
R1034	VRS-CY1JF123F	J	12k	1/16W	Metal Oxide	AA
R1102	VRS-CY1JF113F	J	11k	1/16W	Metal Oxide	AA
R1104	VRS-CA1JF333J	J	33k	1/16W	Metal Oxide	AA
R1106	VRS-CF1JP333JY	J	33k	1/16W	Metal Oxide	AC
R1107	VRS-CY1JF123F	J	12k	1/16W	Metal Oxide	AA
R1108	VRS-CY1JF123F	J	12k	1/16W	Metal Oxide	AA

DUNTKB148FE52
MAIN UNIT (Continued)

Ref. No.	Part No.	★			Description	Code
R1109	VRS-CY1JF333J	J	33k	1/16W	Metal Oxide	AA
R1110	VRS-CY1JF683F	J	68k	1/16W	Metal Oxide	AA
R1111	VRS-CY1JF683F	J	68k	1/16W	Metal Oxide	AA
R1112	VRS-CY1JF113F	J	11k	1/16W	Metal Oxide	AA
R1114	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1115	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R1116	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R1117	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R1118	VRS-CY1JF563F	J	56k	1/16W	Metal Oxide	AA
R1119	VRS-CY1JF472F	J	4.7k	1/16W	Metal Oxide	AA
R1120	VRS-TX2HF5R6J	J	5.6	1/2W	Metal Oxide	AA
R1121	VRS-CY1JF181J	J	180	1/16W	Metal Oxide	AA
R1123	VRS-CY1JF181J	J	180	1/16W	Metal Oxide	AA
R1124	VRS-CY1JF472F	J	4.7k	1/16W	Metal Oxide	AA
R1125	VRS-TX2HF101J	J	100	1/2W	Metal Oxide	AA
R1126	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1127	VRS-TX2HF1R8JY	J	1.8	1/2W	Metal Oxide	AB
R1128	VRS-CY1JF105J	J	1M	1/16W	Metal Oxide	AA
R1129	VRS-CY1JF363F	J	36k	1/16W	Metal Oxide	AA
R1130	VRS-TX2HF5R6J	J	5.6	1/2W	Metal Oxide	AA
R1131	VRS-CY1JF105J	J	1M	1/16W	Metal Oxide	AA
R1132	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1134	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1140	VRS-CY1JF273F	J	27k	1/16W	Metal Oxide	AA
R1142	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1143	VRS-CY1JF391J	J	390	1/16W	Metal Oxide	AA
R1144	VRS-CY1JF391J	J	390	1/16W	Metal Oxide	AA
R1145	VRS-TW2ED5R6J	J	5.6	1/4W	Metal Oxide	AA
R1146	VRS-TW2ED8R2J	J	8.2	1/4W	Metal Oxide	AB
R1147	VRS-TX2HF000J	J	0	1/2W	Metal Oxide	AA
R1148	VRS-TX2HF100J	J	10	1/2W	Metal Oxide	AA
R1150	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1151	VRS-CY1JF123F	J	12k	1/16W	Metal Oxide	AA
R1152	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1153	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1154	VRS-CY1JF683F	J	68k	1/16W	Metal Oxide	AA
R1155	VRS-CY1JF683J	J	68k	1/16W	Metal Oxide	AA
R1156	VRS-CY1JF683F	J	68k	1/16W	Metal Oxide	AA
R1157	VRS-CY1JF104J	J	100k	1/16W	Metal Oxide	AA
R1158	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1160	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1161	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1162	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1163	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1164	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1166	VRS-CY1JF683F	J	68k	1/16W	Metal Oxide	AA
R1167	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1168	VRS-CY1JF123F	J	12k	1/16W	Metal Oxide	AA
R1169	VRS-CF1JP333JY	J	33k	1/16W	Metal Oxide	AC
R1170	VRS-CY1JF683F	J	68k	1/16W	Metal Oxide	AA
R1171	VRS-CY1JF113F	J	11k	1/16W	Metal Oxide	AA
R1172	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1173	VRS-CY1JF333J	J	33k	1/16W	Metal Oxide	AA
R1174	VRS-CY1JF683F	J	68k	1/16W	Metal Oxide	AA
R1175	VRS-CY1JF123F	J	12k	1/16W	Metal Oxide	AA
R1176	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1177	VRS-CY1JF683F	J	68k	1/16W	Metal Oxide	AA
R1178	VRS-CY1JF123F	J	12k	1/16W	Metal Oxide	AA
R1179	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1182	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R1183	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R1184	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R1185	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R1186	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R1187	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R1188	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R1190	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1191	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1192	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1193	VRS-CY1JF680J	J	68	1/16W	Metal Oxide	AA
R1194	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1195	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1196	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1198	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1199	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1201	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1202	VRS-CF1JP220JY	J	22	1/16W	Metal Oxide	AC
R1203	VRS-CF1JP220JY	J	22	1/16W	Metal Oxide	AC
R1204	VRS-CF1JP220JY	J	22	1/16W	Metal Oxide	AC
R1208	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R1209	VRS-CA1JF220J	J	22	1/16W	Metal Oxide	AA
R1210	VRS-CY1JF220J	J	22	1/16W	Metal Oxide	AA
R1211	VRS-CY1JF221J	J	220	1/16W	Metal Oxide	AA
R1212	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1214	VRS-CB1JF101J	J	100	1/16W	Metal Oxide	AA
R1217	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R1218	VRS-CA1JF101J	J	100	1/16W	Metal Oxide	AA
R1220	VRS-CY1JF472J	J	4.7k	1/16W	Metal Oxide	AA
R1221	VRS-CB1JF332J	J	3.3k	1/16W	Metal Oxide	AC
R1222	VRS-CB1JF000J	J	0	1/16W	Metal Oxide	AC
R1223	VRS-CA1JF101J	J	100	1/16W	Metal Oxide	AA
R1225	VRS-CY1JF472J	J	4.7k	1/16W	Metal Oxide	AA
R1226	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R1228	VRS-TX2HF330J	J	33	1/2W	Metal Oxide	AA
R1230	VRS-TV1JD562J	J	5.6k	1/16W	Metal Oxide	AA
R1231	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1232	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R1233	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R1234	VRS-CY1JF472J	J	4.7k	1/16W	Metal Oxide	AA
R1237	VRS-TX2HF472J	J	4.7k	1/2W	Metal Oxide	AA
R1238	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R1240	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1243	VRS-CY1JF1R0J	J	1	1/16W	Metal Oxide	AA
R1245	VRS-CY1JF272J	J	2.7k	1/16W	Metal Oxide	AA
R1246	VRS-CY1JF272J	J	2.7k	1/16W	Metal Oxide	AA
R1247	VRS-CY1JF682J	J	6.8k	1/16W	Metal Oxide	AA
R1248	VRS-CY1JF562J	J	5.6k	1/16W	Metal Oxide	AA
R1249	VRS-CY1JF103J	J	10k	1/16W	Metal Oxide	AA
R1250	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1251	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1252	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1259	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R2001	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R2002	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R2003	VRS-CA1JF223J	J	22k	1/16W	Metal Oxide	AA
R2004	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R2006	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R2007	VRS-CY1JF223J	J	22k	1/16W	Metal Oxide	AA
R2008	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R2009	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R2010	VRS-CA1JF101J	J	100	1/16W	Metal Oxide	AA
R2011	VRS-CB1JF101J	J	100	1/16W	Metal Oxide	AA
R2012	VRS-CA1JF101J	J	100	1/16W	Metal Oxide	AA
R2013	VRS-CA1JF223J	J	22k	1/16W	Metal Oxide	AA
R2014	VRS-CA1JF101J	J	100	1/16W	Metal Oxide	AA
R2015	VRS-CB1JF100J	J	10	1/16W	Metal Oxide	AA
R2017	VRS-CA1JF102J	J	1k	1/16W	Metal Oxide	AA
R2018	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R2019	VRS-CY1JF471J	J	470	1/16W	Metal Oxide	AA
R2020	VRS-CY1JF105J	J	1M	1/16W	Metal Oxide	AA
R2021	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R2022	VRS-CB1JF101J	J	100	1/16W	Metal Oxide	AA
R2025	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R2026	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R2027	VRS-CY1JF223J	J	22k	1/16W	Metal Oxide	AA
R2028	VRS-CB1JF101J	J	100	1/16W	Metal Oxide	AA
R2029	VRS-CY1JF223J	J	22k	1/16W	Metal Oxide	AA
R2030	VRS-CA1JF333J	J	33k	1/16W	Metal Oxide	AA
R2031	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R2032	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R2033	VRS-CB1JF101J	J	100	1/16W	Metal Oxide	AA
R2035	VRS-CY1JF393J	J	39k	1/16W	Metal Oxide	AA
R2036	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R2037	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R2038	VRS-CY1JF103J	J	10k	1/16W	Metal Oxide	AA
R2039	VRS-CA1JF103J	J	10k	1/16W	Metal Oxide	AA
R2041	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R2042	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA

DUNTKB148FE52
MAIN UNIT (Continued)

Ref. No.	Part No.	★	Description			Code
R2043	VRS-CY1JF472J	J	4.7k	1/16W	Metal Oxide	AA
R2044	VRS-CY1JF472J	J	4.7k	1/16W	Metal Oxide	AA
R2052	VRS-CY1JF223J	J	22k	1/16W	Metal Oxide	AA
R2064	VRS-CY1JF223J	J	22k	1/16W	Metal Oxide	AA
R2068	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R2072	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R2078	VRS-CY1JF223J	J	22k	1/16W	Metal Oxide	AA
R3700	VRS-CY1JF472J	J	4.7k	1/16W	Metal Oxide	AA
R3701	VRS-TW2ED1R0J	J	1	1/4W	Metal Oxide	AB
R3702	VRS-TW2ED102J	J	1k	1/4W	Metal Oxide	AA
R3703	VRS-CY1JF274J	J	270k	1/16W	Metal Oxide	AA
R3704	VRS-CY1JF133F	J	13k	1/16W	Metal Oxide	AA
R3705	VRS-CY1JF184J	J	180k	1/16W	Metal Oxide	AA
R3706	VRS-CY1JF100J	J	10	1/16W	Metal Oxide	AA
R3707	VRS-CY1JF105J	J	1M	1/16W	Metal Oxide	AA
R3708	VRS-CY1JF682J	J	6.8k	1/16W	Metal Oxide	AA
R3709	VRS-CY1JF272F	J	2.7k	1/16W	Metal Oxide	AA
R3710	VRS-CY1JF123F	J	12k	1/16W	Metal Oxide	AA
R3711	VRS-CY1JF152F	J	1.5k	1/16W	Metal Oxide	AA
R3712	VRS-CY1JF683F	J	68k	1/16W	Metal Oxide	AA
R3713	VRS-CY1JF563F	J	56k	1/16W	Metal Oxide	AA
R3714	VRS-CY1JF473J	J	47k	1/16W	Metal Oxide	AA
R3715	VRS-CY1JF103J	J	10k	1/16W	Metal Oxide	AA
R3716	VRS-TX2HF000J	J	0	1/2W	Metal Oxide	AA
R3718	VRS-CE3AF821J	J	820	1W	Metal Oxide	AC
R3721	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R3722	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R3724	VRS-CY1JF1R0J	J	1	1/16W	Metal Oxide	AA
R3725	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R3726	VRS-TQ2BD683J	J	68k	1/8W	Metal Oxide	AA
R3727	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R3728	VRS-CY1JF393J	J	39k	1/16W	Metal Oxide	AA
R3729	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R3730	VRS-CY1JF223J	J	22k	1/16W	Metal Oxide	AA
R3731	VRS-CY1JF222J	J	2.2k	1/16W	Metal Oxide	AA
R3732	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R3733	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R3734	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R3735	VRS-CY1JF123F	J	12k	1/16W	Metal Oxide	AA
R3736	VRS-CY1JF223F	J	22k	1/16W	Metal Oxide	AA
R3737	VRS-CY1JF103J	J	10k	1/16W	Metal Oxide	AA
R3738	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R3739	VRS-CY1JF622F	J	6.2k	1/16W	Metal Oxide	AA
R3740	VRS-CY1JF473F	J	47k	1/16W	Metal Oxide	AA
R3741	VRS-CY1JF113F	J	11k	1/16W	Metal Oxide	AA
R3742	VRS-CY1JF182F	J	1.8k	1/16W	Metal Oxide	AA
R3743	VRS-CY1JF122F	J	1.2k	1/16W	Metal Oxide	AA
R3745	VRS-CY1JF682F	J	6.8k	1/16W	Metal Oxide	AA
R3746	VRS-CY1JF122F	J	1.2k	1/16W	Metal Oxide	AA
R3749	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R3750	VRS-CY1JF391J	J	390	1/16W	Metal Oxide	AA
R3751	VRS-TV1JD103J	J	10k	1/16W	Metal Oxide	AA
R3752	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R3759	VRS-TW2ED102J	J	1k	1/4W	Metal Oxide	AA
R3762	VRS-TW2ED561J	J	560	1/4W	Metal Oxide	AA
R3766	VRS-CY1JF472J	J	4.7k	1/16W	Metal Oxide	AA
R7003	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R7018	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R7020	VRS-CB1JF000J	J	0	1/16W	Metal Oxide	AC
R7021	VRS-CB1JF000J	J	0	1/16W	Metal Oxide	AC
R7022	VRS-CB1JF000J	J	0	1/16W	Metal Oxide	AC
R7023	VRS-CB1JF000J	J	0	1/16W	Metal Oxide	AC
R7024	VRS-CA1JF000J	J	0	1/16W	Metal Oxide	AB

MISCELLANEOUS PARTS

FB801	RBLN-0090CEZZ	J	Ferrite Bead	AD
FB802	RBLN-0090CEZZ	J	Ferrite Bead	AD
FB1201	RBLN-0090CEZZ	J	Ferrite Bead	AD
FB1202	RBLN-0006TAZZ	J	Ferrite Bead	AB
FB1203	RBLN-0076TAZZ	J	Ferrite Bead	AC
FB3700	RBLN-0095CEZZ	J	Ferrite Bead	AD
FB3701	RBLN-0095CEZZ	J	Ferrite Bead	AD
FB3704	RBLN-0051TAZZ	J	Ferrite Bead	AC
FB3705	RBLN-0051TAZZ	J	Ferrite Bead	AC
FB3706	RBLN-0254TAZZY	J	Ferrite Bead	AB
FB3707	RBLN-0254TAZZY	J	Ferrite Bead	AB
FB3708	RBLN-0051TAZZ	J	Ferrite Bead	AC
FB3709	RBLN-0095CEZZ	J	Ferrite Bead	AD
P2002	QPLGN1320REZZ	J	Plug, 13-pin(MC)	AC
P2003	QPLGN1258REZZ	J	Plug, 12-pin(MS)	AE
P3702	QPLGN1178GEZZ	J	Plug	AC
SC1201	QSOCNA002WJPZY	J	Socket, 20-pin(LK)	AD
SC1202	QSOCN0687FJZZY	J	Socket, 50-pin(LS)	AF
SC1203	QSOCN0206FJZZ	J	Socket, 30-pin(LG)	AF
SC2001	QSOCN0464FJZZ	J	Socket, 50-pin(MA)	AH
SC2002	QSOCN0487FJZZ	J	Socket, 20-pin(MT)	AE

DUNTKB149DE02
TUNER UNIT

TUNER

NOTE: THE PARTS HERE SHOWN ARE SUPPLIED AS AN ASSEMBLY BUT NOT INDEPENDENTLY.

TU1	VTUVT4T5FD531	J	Tuner	BL

INTEGRATED CIRCUITS

IC304	VHiBH3543F+-1	J	BH3543F-E2	AE
IC1601	VHiSDA5550M-1Q	J	SDA5550M	AZ
IC1602	RH-iXA134WJN2Q	J	I.C.	AY
IC1603	VHi62S8308X-1Q	J	A62S8308X-70SI	AY
IC1604	VHiMM1501XN-1Y	J	MM1501XNRE	AE
IC1605	VHi7WH157FK-1Y	J	TC7WH157FK	AF
IC1606	VHiBA033FP/-1	J	BA033FP-E2	AG
IC1607	VHiPST9121N-1Y	J	IC-PST9121NR	AE
IC1608	VHiLVC157T+-1Y	J	SN74LVC157APWR	AF
IC1609	VHiLVC04AT+-1Y	J	SN74LVC04APWR	AE
IC1610	VHiBA05FP++-1Y	J	BA05FP	AF
IC1611	VHiPST9128N-1Y	J	IC-PST9128NR	AE
IC1612	VHiNC7SZ08P-1Y	J	I.C.	AD
IC1613	VHiBA025FP+-1Y	J	BA25BC0FP	AG
IC1614	VHiTCVHC08T-1Y	J	TC74VHC08FT	AF
IC1615	VHi74LVX86T-1Y	J	TC74LVX86FT	AF
IC1616	VHiNC7SZ58P-1Y	J	NC7SZ58P6X	AE
IC1619	VHiTK15420/-1	J	TK15420MTL	AG
IC1620	VHiTK15420/-1	J	TK15420MTL	AG
IC1901	RH-iX3371CEZZ	J	MSP3410G-QA-B5	BD
IC1902	VHiNJM4560M-1	J	NJM4560M	AG
IC1903	VHiNJM4560M-1	J	NJM4560M	AG
IC2200	VHiMM1506XN-1	J	MM1506XNRE	AE
IC3101	VHiBU4053V/-1	J	BU4053BCFV-E2	AE
IC3305	VHiLA4635A+-1S	J	LA4635A	AM
IC3500	VHiNJM4560M-1	J	NJM4560M	AG

TRANSISTORS

Q302	VSDTC144EKA-1	J	DTC144EKA	AB
Q1606	VS2SC3928AR-1	J	2SC3928AR	AB
Q1607	VS2SA1530AR-1	J	2SA1530AR	AB
Q1608	VSDTC144TE/-1	J	DTC144TE	AB
Q1612	VS2SA1530AR-1	J	2SA1530AR	AB
Q1631	VS2SC3928AR-1	J	2SC3928AR	AB
Q1632	VS2SC3928AR-1	J	2SC3928AR	AB
Q1633	VS2SC3928AR-1	J	2SC3928AR	AB
Q2200	VS2SC3928AR-1	J	2SC3928AR	AB
Q2201	VS2SC3928AR-1	J	2SC3928AR	AB
Q2202	VS2SC3928AR-1	J	2SC3928AR	AB
Q2203	VS2SC3928AR-1	J	2SC3928AR	AB
Q2204	VS2SC3928AR-1	J	2SC3928AR	AB
Q2205	VS2SC3928AR-1	J	2SC3928AR	AB
Q3010	VS2SA1530AR-1	J	2SA1530AR	AB
Q3304	VSDTC314TK/-1	J	DTC314TK	AC
Q3305	VSDTC314TK/-1	J	DTC314TK	AC
Q3306	VS2SC3928AR-1	J	2SC3928AR	AB
Q3307	VSDTC314TK/-1	J	DTC314TK	AC
Q3308	VSDTA144EE/-1	J	DTA144EE	AA
Q3600	VSUPA606T//-1	J	UPA606T	AD

DUNTKB149DE02
TUNER UNIT (Continued)

Ref. No.	Part No.	★	Description	Code
Q3601	VSUPA606T//-1	J	UPA606T	AD
Q3650	VSDTC114YE/-1	J	DTC114YE	AB
Q3906	VSDTC314TK/-1	J	DTC314TK	AC
Q3907	VSDTC314TK/-1	J	DTC314TK	AC
Q3908	VSDTC314TK/-1	J	DTC314TK	AC
Q3909	VSDTC314TK/-1	J	DTC314TK	AC
Q3910	VS2SC3928AR-1	J	2SC3928AR	AB
Q3911	VS2SA1530AR-1	J	2SA1530AR	AB

DIODES

D301	VHDMA3120WA-1	J	Diode	AK
D302	VHDMA3120WA-1	J	Diode	AK
D303	VHDDAN222//-1	J	Diode	AA
D2200	RH-EX1264CEZZ	J	Zener Diode	AB
D2201	RH-EX0906CEZZ	J	Zener Diode	AD
D3301	VHDDAN222//-1	J	Diode	AA
D3302	RH-EX1396CEZZY	J	Zener Diode	AB
D3403	RH-EX1271CEZZ	J	Zener Diode	AB
D3404	RH-EX1271CEZZ	J	Zener Diode	AB
D3412	RH-EX1271CEZZ	J	Zener Diode	AB
D3493	RH-EX1271CEZZ	J	Zener Diode	AB
D3600	VHDiMN10///-1	J	Diode	AB
D3601	VHDiMN10///-1	J	Diode	AB
D3604	VHDiMN10///-1	J	Diode	AB
D3605	VHDiMN10///-1	J	Diode	AB
D3902	RH-EX1247CEZZY	J	Zener Diode	AB
D3905	VHDDAN222//-1	J	Diode	AA
D3908	RH-EX1247CEZZY	J	Zener Diode	AB
D3911	RH-EX1271CEZZ	J	Zener Diode	AB
D3912	VHDDAN222//-1	J	Diode	AA
D5701	RH-EX1271CEZZ	J	Zener Diode	AB

PACKAGED CIRCUITS

X1601	RCRSB0202GEZZ	J	Crystal	AG
X1901	RCRSB0250GEZZ	J	Crystal	AG

COILS

L1601	VP-1M270J3R8N	J	Peaking 27µH	AC
L1901	VP-1M4R7J1R2N	J	Peaking 4.7µH	AB
L1902	VP-1M101J7R7N	J	Peaking 100µH	AC
L2200	VP-1M4R7J1R2N	J	Peaking 4.7µH	AB
L2201	VP-1M2R7JR85NY	J	Peaking 2.7µH	AB
L2202	VP-1M4R7J1R2N	J	Peaking 4.7µH	AB
L2203	VP-1M3R3JR93N	J	Peaking 3.3µH	AB
L2204	VP-1M5R6J1R2NY	J	Peaking 5.6µH	AB
L2205	VP-1M3R3JR93N	J	Peaking 3.3µH	AB
L2206	VP-1M4R7J1R2N	J	Peaking 4.7µH	AB
L2207	VP-1M2R7JR85NY	J	Peaking 2.7µH	AB
L2208	VP-1M4R7J1R2N	J	Peaking 4.7µH	AB
L2210	VP-1M100J1R6N	J	Peaking 10µH	AC
L3202	RCiLC0141CEZZ	J	Coil	AF

CAPACITORS

C334	VCKYTV1CF105Z	J	1	16V	Ceramic	AB
C335	VCKYCY1HB682K	J	6800p	50V	Ceramic	AA
C336	VCKYCY1HB682K	J	6800p	50V	Ceramic	AA
C338	VCKYTV1CF105Z	J	1	16V	Ceramic	AB
C339	VCEAPF0JW476M	J	47	6.3V	Electrolytic	AB
C340	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C341	VCEAPF1CW476M	J	47	16V	Electrolytic	AC
C342	VCEAPF1CW476M	J	47	16V	Electrolytic	AC
C343	VCEAPF1HW225M	J	2.2	50V	Electrolytic	AB
C344	VCEAPF1CW106M	J	10	16V	Electrolytic	AB
C1601	VCEAPF0JW107M	J	100	6.3V	Electrolytic	AC
C1602	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1603	VCKYCY1HB103K	J	0.01	50V	Ceramic	AA
C1604	VCKYCY1HB103K	J	0.01	50V	Ceramic	AA
C1605	VCE9PF0JW226M	J	22	6.3V	Elect. (N.P)	AD
C1606	VCEAPF1EW106M	J	10	25V	Electrolytic	AB
C1608	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C1609	VCKYCY1CF334Z	J	0.33	16V	Ceramic	AA
C1610	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1611	VCEAPF0JW476M	J	47	6.3V	Electrolytic	AB
C1612	VCEAPF1CW106M	J	10	16V	Electrolytic	AB
C1613	VCEAPF1CW226M	J	22	16V	Electrolytic	AB
C1614	VCEAPF0JW107M	J	100	6.3V	Electrolytic	AC
C1616	VCCCCY1HH181J	J	180p	50V	Ceramic	AA
C1617	VCEAPF0JW226M	J	22	6.3V	Electrolytic	AB
C1618	VCEAPF0JW476M	J	47	6.3V	Electrolytic	AB
C1619	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1621	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1622	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1623	VCE9PF0JW226M	J	22	6.3V	Elect. (N.P)	AD
C1624	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1625	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1626	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1627	VCKYTV1CF105Z	J	1	16V	Ceramic	AB
C1628	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1631	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1633	VCCCCY1HH330J	J	33p	50V	Ceramic	AA
C1634	VCCCCY1HH330J	J	33p	50V	Ceramic	AA
C1635	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1636	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1637	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1638	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1639	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1640	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1641	VCEAPF0JW226M	J	22	6.3V	Electrolytic	AB
C1642	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1644	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1645	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1646	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1647	VCKYCY1CF334Z	J	0.33	16V	Ceramic	AA
C1648	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1649	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1650	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1653	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1655	VCE9PF0JN226MY	J	22	6.3V	Elect. (N.P)	AD
C1656	VCE9PF0JN226MY	J	22	6.3V	Elect. (N.P)	AD
C1657	VCE9PF0JN226MY	J	22	6.3V	Elect. (N.P)	AD
C1658	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1659	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1660	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1661	VCEAPF1CW107M	J	100	16V	Electrolytic	AD
C1662	VCEAPF0JW107M	J	100	6.3V	Electrolytic	AC
C1663	VCEAPF1CW106M	J	10	16V	Electrolytic	AB
C1664	VCEAPF1CW106M	J	10	16V	Electrolytic	AB
C1665	VCEAPF1CW106M	J	10	16V	Electrolytic	AB
C1666	VCKYCY1HB561K	J	560p	50V	Ceramic	AA
C1667	VCKYCY1HB561K	J	560p	50V	Ceramic	AA
C1668	VCKYCY1HB561K	J	560p	50V	Ceramic	AA
C1900	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1901	VCKYCY1HB102K	J	1000p	50V	Ceramic	AA
C1902	VCKYCY1HB102K	J	1000p	50V	Ceramic	AA
C1903	VCKYCY1HB472K	J	4700p	50V	Ceramic	AA
C1904	VCKYCY1HB223K	J	0.022	50V	Ceramic	AB
C1905	VCKYCY1HB682K	J	6800p	50V	Ceramic	AA
C1906	VCKYCY1HB682K	J	6800p	50V	Ceramic	AA
C1907	VCEAPF1CW106M	J	10	16V	Electrolytic	AB
C1908	VCEAPF1CW106M	J	10	16V	Electrolytic	AB
C1909	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1910	RC-EZ0417CEZZ	J	150	16V	Electrolytic	AD
C1911	VCEAPF1HW335M	J	3.3	50V	Electrolytic	AB
C1912	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1913	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C1914	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C1915	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C1916	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C1917	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1918	VCEAPF1CW106M	J	10	16V	Electrolytic	AB
C1919	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C1920	VCCCCY1HH560J	J	56p	50V	Ceramic	AA
C1921	VCCCCY1HH560J	J	56p	50V	Ceramic	AA
C1922	VCCCCY1HH560J	J	56p	50V	Ceramic	AA
C1923	VCCCCY1HH5R0C	J	5p	50V	Ceramic	AA
C1924	VCCCCY1HH5R0C	J	5p	50V	Ceramic	AA
C1925	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1926	RC-EZ0417CEZZ	J	150	16V	Electrolytic	AD

DUNTKB149DE02
TUNER UNIT (Continued)

Ref. No.	Part No.	★			Description	Code
C1928	RC-EZ0417CEZZ	J	150	16V	Electrolytic	AD
C1929	RC-EZ0417CEZZ	J	150	16V	Electrolytic	AD
C1930	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C1931	VCKYCY1HB681K	J	680p	50V	Ceramic	AA
C1932	VCKYCY1HB681K	J	680p	50V	Ceramic	AA
C1933	VCKYCY1HB472K	J	4700p	50V	Ceramic	AA
C1935	RC-EZ1339CEZZ	J	220	16V	Electrolytic	AD
C1936	VCEAPF1HW225M	J	2.2	50V	Electrolytic	AB
C1937	VCEAPF1HW225M	J	2.2	50V	Electrolytic	AB
C1938	VCEAPF1CW106M	J	10	16V	Electrolytic	AB
C1939	VCKYTV1CF105Z	J	1	16V	Ceramic	AB
C1940	VCKYTV1CF105Z	J	1	16V	Ceramic	AB
C1941	VCEAPF1EW475M	J	4.7	25V	Electrolytic	AB
C1942	VCEAPF1EW475M	J	4.7	25V	Electrolytic	AB
C1943	VCKYCY1HB102K	J	1000p	50V	Ceramic	AA
C1944	VCKYCY1HB102K	J	1000p	50V	Ceramic	AA
C1945	VCKYCY1HB102K	J	1000p	50V	Ceramic	AA
C1946	VCKYCY1HB102K	J	1000p	50V	Ceramic	AA
C1947	VCKYTV1CF105Z	J	1	16V	Ceramic	AB
C1948	VCKYCY1HB223K	J	0.022	50V	Ceramic	AB
C1960	VCCCCY1HH101J	J	100p	50V	Ceramic	AA
C1961	VCCCCY1HH101J	J	100p	50V	Ceramic	AA
C2200	VCEAPW1CN477M	J	470	16V	Electrolytic	AE
C2201	VCKYCY1HB103K	J	0.01	50V	Ceramic	AA
C2202	VCCCCY1HH560J	J	56p	50V	Ceramic	AA
C2203	VCCCCY1HH560J	J	56p	50V	Ceramic	AA
C2204	VCCCCY1HH271J	J	270p	50V	Ceramic	AA
C2205	VCCCCY1HH121J	J	120p	50V	Ceramic	AA
C2206	VCCCCY1HH820J	J	82p	50V	Ceramic	AA
C2207	VCCCCY1HH180J	J	18p	50V	Ceramic	AA
C2208	VCCCCY1HH151J	J	150p	50V	Ceramic	AA
C2209	VCCCCY1HH121J	J	120p	50V	Ceramic	AA
C2210	VCKYCY1HB103K	J	0.01	50V	Ceramic	AA
C2211	VCEAPF1CW476M	J	47	16V	Electrolytic	AC
C2212	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C2213	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C2214	VCEAPF0JW107M	J	100	6.3V	Electrolytic	AC
C2215	VCCCCY1HH101J	J	100p	50V	Ceramic	AA
C2216	VCCCCY1HH101J	J	100p	50V	Ceramic	AA
C2217	VCEAPW0JN477M	J	470	6.3V	Electrolytic	AE
C2218	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C2219	VCKYCY1HF103Z	J	0.01	50V	Ceramic	AA
C2220	VCKYCY1HB102K	J	1000p	50V	Ceramic	AA
C2221	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C2222	VCEAPF1CW106M	J	10	16V	Electrolytic	AB
C2223	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C2224	VCKYCY1HB103K	J	0.01	50V	Ceramic	AA
C2225	VCEAPF1HW105M	J	1	50V	Electrolytic	AB
C2226	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C2227	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C2228	VCE9PF1CW106M	J	10	16V	Elect. (N.P)	AC
C2229	VCCCCY1HH331J	J	330p	50V	Ceramic	AA
C3201	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C3202	RC-EZ1351CEZZ	J	3300	6.3V	Electrolytic	AF
C3359	VCEAPF1CW106M	J	10	16V	Electrolytic	AB
C3360	VCEAPF1CW107M	J	100	16V	Electrolytic	AD
C3361	VCEAPF1HW105M	J	1	50V	Electrolytic	AB
C3362	VCKYCY1HB102K	J	1000p	50V	Ceramic	AA
C3363	VCEAPF1HW225M	J	2.2	50V	Electrolytic	AB
C3364	VCEAPF1HW105M	J	1	50V	Electrolytic	AB
C3365	VCKYCY1HB102K	J	1000p	50V	Ceramic	AA
C3366	VCEAPF1HW225M	J	2.2	50V	Electrolytic	AB
C3367	VCEAPF1CW106M	J	10	16V	Electrolytic	AB
C3368	VCEAPF1CW106M	J	10	16V	Electrolytic	AB
C3369	RC-EZ1274CEZZ	J	1000	16V	Electrolytic	AD
C3370	VCKYTV1CF105Z	J	1	16V	Ceramic	AB
C3371	RC-EZ1274CEZZ	J	1000	16V	Electrolytic	AD
C3372	RC-EZ1274CEZZ	J	1000	16V	Electrolytic	AD
C3373	RC-EZ1274CEZZ	J	1000	16V	Electrolytic	AD
C3500	VCKYCY1HB682K	J	6800p	50V	Ceramic	AA
C3501	VCKYCY1HB682K	J	6800p	50V	Ceramic	AA
C3502	VCKYTV1CF105Z	J	1	16V	Ceramic	AB
C3503	VCKYTV1CF105Z	J	1	16V	Ceramic	AB
C3504	VCEAPF1CW106M	J	10	16V	Electrolytic	AB
C3505	VCEAPF1EW475M	J	4.7	25V	Electrolytic	AB
C3506	VCEAPF1EW475M	J	4.7	25V	Electrolytic	AB
C3507	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA
C3508	RC-EZ0417CEZZ	J	150	16V	Electrolytic	AD
C3517	VCKYCY1EB223K	J	0.022	25V	Ceramic	AA
C3518	VCKYCY1EB223K	J	0.022	25V	Ceramic	AA
C3525	VCCCCY1HH101J	J	100p	50V	Ceramic	AA
C3526	VCCCCY1HH101J	J	100p	50V	Ceramic	AA
C3600	VCKYTQ1EF105Z	J	1	25V	Ceramic	AD
C3601	VCKYTQ1EF105Z	J	1	25V	Ceramic	AD
C3602	VCKYTQ1EF105Z	J	1	25V	Ceramic	AD
C3603	VCKYTQ1EF105Z	J	1	25V	Ceramic	AD
C3900	VCCCCY1HH221J	J	220p	50V	Ceramic	AA
C3901	VCCCCY1HH221J	J	220p	50V	Ceramic	AA
C3902	VCCCCY1HH221J	J	220p	50V	Ceramic	AA
C3903	VCCCCY1HH221J	J	220p	50V	Ceramic	AA
C3954	VCEAPF1CW106M	J	10	16V	Electrolytic	AB
C3955	VCEAPF1CW106M	J	10	16V	Electrolytic	AB
C3956	VCCCCY1HH101J	J	100p	50V	Ceramic	AA
C3957	VCCCCY1HH101J	J	100p	50V	Ceramic	AA
C3958	VCEAPF1CW106M	J	10	16V	Electrolytic	AB
C3959	VCEAPF1CW106M	J	10	16V	Electrolytic	AB
C3960	VCEAPF1CW106M	J	10	16V	Electrolytic	AB
C3961	VCEAPF1CW476M	J	47	16V	Electrolytic	AC
C3962	VCEAPF1CW476M	J	47	16V	Electrolytic	AC
C3995	VCKYCY1EF104Z	J	0.1	25V	Ceramic	AA

RESISTORS

Ref. No.	Part No.	★			Description	Code
R345	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R346	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R347	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R350	VRS-CY1JF392J	J	3.9k	1/16W	Metal Oxide	AA
R351	VRS-CY1JF392J	J	3.9k	1/16W	Metal Oxide	AA
R352	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R353	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R354	VRS-CY1JF472J	J	4.7k	1/16W	Metal Oxide	AA
R355	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R358	VRS-CY1JF123J	J	12k	1/16W	Metal Oxide	AA
R1602	VRS-CY1JF202J	J	2k	1/16W	Metal Oxide	AA
R1603	VRS-CY1JF202J	J	2k	1/16W	Metal Oxide	AA
R1605	VRS-CY1JF332J	J	3.3k	1/16W	Metal Oxide	AA
R1609	VRS-CY1JF681J	J	680	1/16W	Metal Oxide	AA
R1610	VRS-TX2HF2R2J	J	2.2	1/2W	Metal Oxide	AB
R1613	VRS-CY1JF132J	J	1.3k	1/16W	Metal Oxide	AA
R1618	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1620	VRS-CY1JF223J	J	22k	1/16W	Metal Oxide	AA
R1621	VRS-CY1JF223J	J	22k	1/16W	Metal Oxide	AA
R1622	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1626	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R1627	VRS-CY1JF102F	J	1k	1/16W	Metal Oxide	AA
R1628	VRS-CY1JF681F	J	680	1/16W	Metal Oxide	AA
R1629	VRS-CY1JF681F	J	680	1/16W	Metal Oxide	AA
R1630	VRS-CY1JF102F	J	1k	1/16W	Metal Oxide	AA
R1631	VRS-CY1JF472F	J	4.7k	1/16W	Metal Oxide	AA
R1632	VRS-CY1JF472F	J	4.7k	1/16W	Metal Oxide	AA
R1633	VRS-CY1JF472F	J	4.7k	1/16W	Metal Oxide	AA
R1636	VRS-CY1JF333J	J	33k	1/16W	Metal Oxide	AA
R1637	VRS-CY1JF103J	J	10k	1/16W	Metal Oxide	AA
R1638	VRS-CY1JF332F	J	3.3k	1/16W	Metal Oxide	AA
R1639	VRS-CY1JF152F	J	1.5k	1/16W	Metal Oxide	AA
R1642	VRS-CY1JF221J	J	220	1/16W	Metal Oxide	AA
R1643	VRS-CY1JF333J	J	33k	1/16W	Metal Oxide	AA
R1644	VRS-CY1JF393F	J	39k	1/16W	Metal Oxide	AA
R1650	VRS-CY1JF332J	J	3.3k	1/16W	Metal Oxide	AA
R1651	VRS-CY1JF561J	J	560	1/16W	Metal Oxide	AA
R1652	VRS-CY1JF561J	J	560	1/16W	Metal Oxide	AA
R1653	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1655	VRS-CY1JF221J	J	220	1/16W	Metal Oxide	AA
R1656	VRS-CY1JF221J	J	220	1/16W	Metal Oxide	AA
R1659	VRS-CY1JF222J	J	2.2k	1/16W	Metal Oxide	AA
R1661	VRS-CY1JF223J	J	22k	1/16W	Metal Oxide	AA
R1662	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1663	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1664	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA

DUNTKB149DE02
TUNER UNIT (Continued)

Ref. No.	Part No.	★			Description	Code
R1665	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1668	VRS-CY1JF332J	J	3.3k	1/16W	Metal Oxide	AA
R1669	VRS-CB1JF332J	J	3.3k	1/16W	Metal Oxide	AC
R1670	VRS-CY1JF473J	J	47k	1/16W	Metal Oxide	AA
R1671	VRS-CY1JF183F	J	18k	1/16W	Metal Oxide	AA
R1675	VRS-CY1JF332J	J	3.3k	1/16W	Metal Oxide	AA
R1683	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R1684	VRS-CY1JF333F	J	33k	1/16W	Metal Oxide	AA
R1685	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R1686	VRS-CY1JF472F	J	4.7k	1/16W	Metal Oxide	AA
R1687	VRS-CY1JF473J	J	47k	1/16W	Metal Oxide	AA
R1688	VRS-CY1JF223F	J	22k	1/16W	Metal Oxide	AA
R1689	VRS-CY1JF473J	J	47k	1/16W	Metal Oxide	AA
R1690	VRS-CY1JF183F	J	18k	1/16W	Metal Oxide	AA
R1691	VRS-CY1JF472F	J	4.7k	1/16W	Metal Oxide	AA
R1692	VRS-CY1JF333F	J	33k	1/16W	Metal Oxide	AA
R1693	VRS-CY1JF223F	J	22k	1/16W	Metal Oxide	AA
R1694	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R1695	VRS-CY1JF183F	J	18k	1/16W	Metal Oxide	AA
R1696	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R1697	VRS-CY1JF223F	J	22k	1/16W	Metal Oxide	AA
R1698	VRS-CY1JF472F	J	4.7k	1/16W	Metal Oxide	AA
R1699	VRS-CY1JF333F	J	33k	1/16W	Metal Oxide	AA
R1901	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R1902	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R1903	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R1905	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R1906	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R1907	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R1908	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R1913	VRS-CY1JF105J	J	1M	1/16W	Metal Oxide	AA
R1914	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1915	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1916	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1917	VRS-CY1JF103F	J	10k	1/16W	Metal Oxide	AA
R1918	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R1919	VRS-CY1JF392J	J	3.9k	1/16W	Metal Oxide	AA
R1920	VRS-CY1JF223J	J	22k	1/16W	Metal Oxide	AA
R1921	VRS-CY1JF223J	J	22k	1/16W	Metal Oxide	AA
R1923	VRS-CY1JF104J	J	100k	1/16W	Metal Oxide	AA
R1925	VRS-CY1JF104J	J	100k	1/16W	Metal Oxide	AA
R1930	VRS-CY1JF153J	J	15k	1/16W	Metal Oxide	AA
R1931	VRS-CY1JF223J	J	22k	1/16W	Metal Oxide	AA
R1932	VRS-CY1JF473J	J	47k	1/16W	Metal Oxide	AA
R1933	VRS-CY1JF473J	J	47k	1/16W	Metal Oxide	AA
R1934	VRS-CY1JF122J	J	1.2k	1/16W	Metal Oxide	AA
R1935	VRS-CY1JF122J	J	1.2k	1/16W	Metal Oxide	AA
R1936	VRS-CY1JF562J	J	5.6k	1/16W	Metal Oxide	AA
R1937	VRS-CY1JF562J	J	5.6k	1/16W	Metal Oxide	AA
R1938	VRS-CY1JF472J	J	4.7k	1/16W	Metal Oxide	AA
R1939	VRS-CY1JF472J	J	4.7k	1/16W	Metal Oxide	AA
R1941	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R1942	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R1943	VRS-CA1JF102J	J	1k	1/16W	Metal Oxide	AA
R1944	VRS-CY1JF471J	J	470	1/16W	Metal Oxide	AA
R1945	VRS-CY1JF471J	J	470	1/16W	Metal Oxide	AA
R1946	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R1947	VRS-CY1JF392J	J	3.9k	1/16W	Metal Oxide	AA
R1948	VRS-CY1JF473J	J	47k	1/16W	Metal Oxide	AA
R1950	VRS-CY1JF473J	J	47k	1/16W	Metal Oxide	AA
R2200	VRS-TX2HF1R0J	J	1	1/2W	Metal Oxide	AA
R2201	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R2202	VRS-CY1JF222J	J	2.2k	1/16W	Metal Oxide	AA
R2203	VRS-CY1JF222J	J	2.2k	1/16W	Metal Oxide	AA
R2204	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R2205	VRS-CY1JF221J	J	220	1/16W	Metal Oxide	AA
R2206	VRS-CY1JF152J	J	1.5k	1/16W	Metal Oxide	AA
R2207	VRS-CY1JF681J	J	680	1/16W	Metal Oxide	AA
R2208	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R2209	VRS-CY1JF181J	J	180	1/16W	Metal Oxide	AA
R2210	VRS-CY1JF561J	J	560	1/16W	Metal Oxide	AA
R2211	VRS-CY1JF103J	J	10k	1/16W	Metal Oxide	AA
R2212	VRS-CY1JF332J	J	3.3k	1/16W	Metal Oxide	AA
R2213	VRS-CY1JF221J	J	220	1/16W	Metal Oxide	AA
R2214	VRS-CY1JF152J	J	1.5k	1/16W	Metal Oxide	AA
R2215	VRS-CY1JF222J	J	2.2k	1/16W	Metal Oxide	AA
R2216	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R2217	VRS-CY1JF222J	J	2.2k	1/16W	Metal Oxide	AA
R2218	VRS-CY1JF221J	J	220	1/16W	Metal Oxide	AA
R2219	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R2221	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R2222	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R2223	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R2224	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R2225	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R2226	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R2227	VRS-CY1JF471J	J	470	1/16W	Metal Oxide	AA
R2228	VRS-CY1JF472J	J	4.7k	1/16W	Metal Oxide	AA
R2229	VRS-CY1JF472J	J	4.7k	1/16W	Metal Oxide	AA
R2230	VRS-TX2HF471J	J	470	1/2W	Metal Oxide	AB
R2231	VRS-TW2ED000J	J	0	1/4W	Metal Oxide	AB
R3100	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R3356	VRS-CY1JF153J	J	15k	1/16W	Metal Oxide	AA
R3357	VRS-TX2HF000J	J	0	1/2W	Metal Oxide	AA
R3358	VRS-CY1JF562J	J	5.6k	1/16W	Metal Oxide	AA
R3360	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R3361	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R3362	VRS-CY1JF182J	J	1.8k	1/16W	Metal Oxide	AA
R3363	VRS-CY1JF182J	J	1.8k	1/16W	Metal Oxide	AA
R3364	VRS-CY1JF122J	J	1.2k	1/16W	Metal Oxide	AA
R3365	VRS-CY1JF472J	J	4.7k	1/16W	Metal Oxide	AA
R3366	VRS-CY1JF472J	J	4.7k	1/16W	Metal Oxide	AA
R3368	VRS-CR3AD1R0J	J	1	1W	Metal Oxide	AC
R3370	VRS-CY1JF223J	J	22k	1/16W	Metal Oxide	AA
R3371	VRS-CY1JF682J	J	6.8k	1/16W	Metal Oxide	AA
R3372	VRS-CY1JF103J	J	10k	1/16W	Metal Oxide	AA
R3373	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R3374	VRS-TX2HF000J	J	0	1/2W	Metal Oxide	AA
R3401	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R3433	VRS-CY1JF750J	J	75	1/16W	Metal Oxide	AA
R3455	VRS-CY1JF750J	J	75	1/16W	Metal Oxide	AA
R3456	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R3457	VRS-CY1JF750J	J	75	1/16W	Metal Oxide	AA
R3458	VRS-CY1JF104J	J	100k	1/16W	Metal Oxide	AA
R3459	VRS-CY1JF750J	J	75	1/16W	Metal Oxide	AA
R3460	VRS-CY1JF750J	J	75	1/16W	Metal Oxide	AA
R3461	VRS-CY1JF750J	J	75	1/16W	Metal Oxide	AA
R3491	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R3492	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R3494	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R3500	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R3501	VRS-CY1JF102J	J	1k	1/16W	Metal Oxide	AA
R3504	VRS-CY1JF122J	J	1.2k	1/16W	Metal Oxide	AA
R3505	VRS-CY1JF682J	J	6.8k	1/16W	Metal Oxide	AA
R3506	VRS-CY1JF122J	J	1.2k	1/16W	Metal Oxide	AA
R3507	VRS-CY1JF682J	J	6.8k	1/16W	Metal Oxide	AA
R3508	VRS-CY1JF471J	J	470	1/16W	Metal Oxide	AA
R3509	VRS-CY1JF471J	J	470	1/16W	Metal Oxide	AA
R3510	VRS-CY1JF473J	J	47k	1/16W	Metal Oxide	AA
R3511	VRS-CY1JF473J	J	47k	1/16W	Metal Oxide	AA
R3512	VRS-CY1JF223J	J	22k	1/16W	Metal Oxide	AA
R3513	VRS-CY1JF153J	J	15k	1/16W	Metal Oxide	AA
R3600	VRS-CB1JF222J	J	2.2k	1/16W	Metal Oxide	AC
R3604	VRS-CB1JF824JY	J	820k	1/16W	Metal Oxide	AC
R3607	VRS-CB1JF562J	J	5.6k	1/16W	Metal Oxide	AC
R3610	VRS-CY1JF563J	J	56k	1/16W	Metal Oxide	AA
R3650	VRS-CY1JF103J	J	10k	1/16W	Metal Oxide	AA
R3962	VRS-CY1JF473J	J	47k	1/16W	Metal Oxide	AA
R3963	VRS-CY1JF473J	J	47k	1/16W	Metal Oxide	AA
R3964	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R3965	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R3966	VRS-CY1JF271J	J	270	1/16W	Metal Oxide	AA
R3967	VRS-CY1JF271J	J	270	1/16W	Metal Oxide	AA
R3968	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R3969	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA
R3970	VRS-CY1JF271J	J	270	1/16W	Metal Oxide	AA
R3971	VRS-CY1JF271J	J	270	1/16W	Metal Oxide	AA
R3972	VRS-CY1JF104J	J	100k	1/16W	Metal Oxide	AA

DUNTKB149DE02 TUNER UNIT (Continued)

Ref. No.	Part No.	★	Description	Code
R3973	VRS-CY1JF104J	J	100k 1/16W Metal Oxide	AA
R3986	VRS-CY1JF104J	J	100k 1/16W Metal Oxide	AA
R3987	VRS-CY1JF562J	J	5.6k 1/16W Metal Oxide	AA
R3989	VRS-CY1JF153J	J	15k 1/16W Metal Oxide	AA
R3991	VRS-CY1JF103J	J	10k 1/16W Metal Oxide	AA
R3992	VRS-CY1JF104J	J	100k 1/16W Metal Oxide	AA
R3993	VRS-CY1JF104J	J	100k 1/16W Metal Oxide	AA
R3994	VRS-CY1JF472J	J	4.7k 1/16W Metal Oxide	AA
R3995	VRS-CY1JF823J	J	82k 1/16W Metal Oxide	AA
R3996	VRS-CY1JF102J	J	1k 1/16W Metal Oxide	AA
R3997	VRS-CY1JF104J	J	100k 1/16W Metal Oxide	AA
R3998	VRS-CY1JF103J	J	10k 1/16W Metal Oxide	AA
R5705	VRS-TQ2BD750J	J	75 1/8W Metal Oxide	AA
R5706	VRS-TQ2BD750J	J	75 1/8W Metal Oxide	AA
R5707	VRS-TQ2BD750J	J	75 1/8W Metal Oxide	AA
R5708	VRS-CY1JF473J	J	47k 1/16W Metal Oxide	AA
R5709	VRS-CY1JF473J	J	47k 1/16W Metal Oxide	AA
R5710	VRS-CY1JF101J	J	100 1/16W Metal Oxide	AA
R5711	VRS-CY1JF101J	J	100 1/16W Metal Oxide	AA
R5712	VRS-CY1JF101J	J	100 1/16W Metal Oxide	AA
R5713	VRS-CY1JF101J	J	100 1/16W Metal Oxide	AA
R5714	VRS-CY1JF101J	J	100 1/16W Metal Oxide	AA

MISCELLANEOUS PARTS

⚠ F1	QFS-C1223CEZZ	J	Fuse, 1.25A/250V	AD
⚠ F2	QFS-C1223CEZZ	J	Fuse, 1.25A/250V	AD
FH1	QFSHD1002CEZZ	J	Fuse Holder	AA
FH2	QFSHD1002CEZZ	J	Fuse Holder	AA
FH3	QFSHD1002CEZZ	J	Fuse Holder	AA
FH4	QFSHD1002CEZZ	J	Fuse Holder	AA
FB1601	RBLN-0006TAZZ	J	Ferrite Bead	AB
FB1602	RBLN-0006TAZZ	J	Ferrite Bead	AB
FB1604	RBLN-0006TAZZ	J	Ferrite Bead	AB
FB1605	RBLN-0006TAZZ	J	Ferrite Bead	AB
FB1608	RBLN-0006TAZZ	J	Ferrite Bead	AB
FB1609	RBLN-0006TAZZ	J	Ferrite Bead	AB
FB1640	RBLN-0076TAZZ	J	Ferrite Bead	AC
FB1641	RBLN-0076TAZZ	J	Ferrite Bead	AC
FB1672	RBLN-0076TAZZ	J	Ferrite Bead	AC
FB1673	RBLN-0076TAZZ	J	Ferrite Bead	AC
FB1674	RBLN-0076TAZZ	J	Ferrite Bead	AC
J3702	QJAKE0193CEZZ	J	POWER INPUT (DC12V)	AK
J3902	QJAKE0200CE02	J	AUDIO OUT (R)	AE
J3903	QJAKE0200CE09	J	AUDIO OUT (L)	AE
J5001	QJAKF0060CEZZ	J	VIDEO (AV-IN2)	AE
J5002	QJAKE0200CE04	J	Headphone	AE
P1903	QPLGN1178GEZZ	J	Plug, 11-pin(MB)	AC
P3301	QPLGN0174FJZZ	J	Plug, 2-pin(SL)	AC
P3302	QPLGN0174FJZZ	J	Plug, 2-pin(SR)	AC
P3601	QPLGN0478GEZZ	J	Plug, 4-pin	AB
P3603	QPLGN0378GEZZ	J	Plug, 3-pin(VE)	AB
P3703	QLUGHA001WJZZY	J	Lug	AD
SC1602	QSOCN0487FJZZ	J	Socket, 20-pin(MT)	AE
SC3100	QSOCN0464FJZZ	J	Socket, 50-pin(MA)	AH
SC3903	QSOCZA012WJZZ	J	Socket, 21-pin(SCART)	AG
SC5001	QSOCD0456CEZZ	J	S-VIDEO (AV-IN2)	AE
	LANGT9102CEFW	J	Fixing Metal	AF
	XWHJZ32-05080	J	Washer, x1	AB
	XBBSF30P08000	J	Screw, x2	AA

DUNTKB150DE02 INVERTER UNIT

TRANSISTORS

Q6500	VSFZT1053A/-1	J	FZT1053A	AG
Q6501	VSFZT1053A/-1	J	FZT1053A	AG
Q6502	VS2SA1530AR-1	J	2SA1530AR	AB
Q6503	VSFZT1053A/-1	J	FZT1053A	AG
Q6504	VSFZT1053A/-1	J	FZT1053A	AG
Q6505	VS2SA1530AR-1	J	2SA1530AR	AB

DIODE

D6500	VHDiMN10///-1	J	Diode	AB

COILS

L6500	RCiLC0107CEZZ	J	Coil	AF
L6501	RCiLC0107CEZZ	J	Coil	AF
L6502	RCiLC0107CEZZ	J	Coil	AF
L6503	RCiLC0107CEZZ	J	Coil	AF

TRANSFORMERS

⚠ T6500	RTRNZ0805CEZZQ	J	Transformer	AM
⚠ T6501	RTRNZ0805CEZZQ	J	Transformer	AM
⚠ T6502	RTRNZ0805CEZZQ	J	Transformer	AM
⚠ T6503	RTRNZ0805CEZZQ	J	Transformer	AM

CAPACITORS

C6502	VCKYCY1CB473K	J	0.047	16V	Ceramic	AA
C6503	VCKYCY1CB473K	J	0.047	16V	Ceramic	AA
C6504	VCEA4A1CN108M	J	1000	16V	Electrolytic	AD
C6507	VCKYCY1CB473K	J	0.047	16V	Ceramic	AA
C6508	VCKYCY1CB473K	J	0.047	16V	Ceramic	AA
C6509	VCEA4A1CN108M	J	1000	16V	Electrolytic	AD
C6510	RC-FZA034WJZZ	J	0.15	250V	Film	AE
C6511	RC-FZA034WJZZ	J	0.15	250V	Film	AE

RESISTORS

R6500	VRS-TW2ED332J	J	3.3k	1/4W	Metal Oxide	AB
R6501	VRS-TW2ED332J	J	3.3k	1/4W	Metal Oxide	AB
R6502	VRS-CY1JF103J	J	10k	1/16W	Metal Oxide	AA
R6503	VRS-CY1JF333J	J	33k	1/16W	Metal Oxide	AA
R6504	VRS-TW2ED332J	J	3.3k	1/4W	Metal Oxide	AB
R6505	VRS-TW2ED332J	J	3.3k	1/4W	Metal Oxide	AB
R6506	VRS-CY1JF103J	J	10k	1/16W	Metal Oxide	AA
R6507	VRS-CY1JF333J	J	33k	1/16W	Metal Oxide	AA

MISCELLANEOUS PARTS

⚠ F6500	QFS-C1223CEZZ	J	Fuse, 1.25A/250V	AD
⚠ F6501	QFS-C1223CEZZ	J	Fuse, 1.25A/250V	AD
FH6500	QFSHD1002CEZZ	J	Fuse Holder	AA
FH6501	QFSHD1002CEZZ	J	Fuse Holder	AA
FH6502	QFSHD1002CEZZ	J	Fuse Holder	AA
FH6503	QFSHD1002CEZZ	J	Fuse Holder	AA
P6500	QPLGN0155FJZZ	J	Plug, 3-pin	AE
P6501	QPLGN0155FJZZ	J	Plug, 3-pin	AE
P6502	QPLGN0378GEZZ	J	Plug, 3-pin(VE)	AB

DUNTKB151DE02 OPERATION UNIT

TRANSISTORS

Q4001	VSDTC144EE/-1	J	DTC144EE	AA
Q4003	VSDTC144EE/-1	J	DTC144EE	AA
Q4007	VSUMG4N++++-1Y	J	UMG4N++++	AB

DIODES

D4008	RH-EX1283CEZZ	J	Zener Diode	AB
D4009	RH-EX1271CEZZ	J	Zener Diode	AB
D4010	RH-EX1271CEZZ	J	Zener Diode	AB
D4011	RH-PX0419CEZZ	J	Remote sensor indicator	AC
D4012	RH-EX1271CEZZ	J	Zener Diode	AB
D4014	RH-PX0421CEZZ	J	Power/Standby indicator	AD
D4015	RH-EX1271CEZZ	J	Zener Diode	AB
D4022	RH-EX1271CEZZ	J	Zener Diode	AB

CAPACITORS

C4018	RC-KZ1025CEZZ	J	1	10V	Ceramic	AB
C4020	VCKYCY1HB222K	J	2200p	50V	Ceramic	AA
C4021	VCKYCY1HB222K	J	2200p	50V	Ceramic	AA

Ref. No.	Part No.	★	Description	Code

DUNTKB151DE02 OPERATION UNIT (Continued)

RESISTORS

R4001	VRS-CY1JF562J	J	5.6k	1/16W	Metal Oxide	AA
R4005	VRS-CY1JF123J	J	12k	1/16W	Metal Oxide	AA
R4006	VRS-CY1JF822J	J	8.2k	1/16W	Metal Oxide	AA
R4011	VRS-CY1JF123J	J	12k	1/16W	Metal Oxide	AA
R4012	VRS-CY1JF822J	J	8.2k	1/16W	Metal Oxide	AA
R4013	VRS-TX2HF220J	J	22	1/2W	Metal Oxide	AB
R4015	VRS-TX2HF220J	J	22	1/2W	Metal Oxide	AB
R4021	VRS-CY1JF101J	J	100	1/16W	Metal Oxide	AA
R4023	VRS-CY1JF472J	J	4.7k	1/16W	Metal Oxide	AA
R4024	VRS-CY1JF471J	J	470	1/16W	Metal Oxide	AA
R4029	VRS-CY1JF472J	J	4.7k	1/16W	Metal Oxide	AA
R4030	VRS-CY1JF000J	J	0	1/16W	Metal Oxide	AA

SWITCHES

S4701	QSW-P0035GEZZ	J	MAIN POWER	AF
SW4002	QSW-K0108CEZZ	J	CH(∨)	AD
SW4003	QSW-K0108CEZZ	J	CH(∧)	AD
SW4004	QSW-K0108CEZZ	J	MENU	AD
SW4006	QSW-K0108CEZZ	J	TV/VIDEO	AD
SW4007	QSW-K0108CEZZ	J	Volume (+)	AD
SW4008	QSW-K0108CEZZ	J	Volume (–)	AD

MISCELLANEOUS PARTS

FB4020	RBLN-0062CEZZ	J	Ferrite Bead	AC
FB4021	RBLN-0062CEZZ	J	Ferrite Bead	AC
J4001	QJAKJ0063CEZZ	J	Headphones Jack	AF
P4004	QPLGN1264TAZZ	J	Plug, 12-pin(MS)	AE
RMC4002	RRMCU0239CEZZ	J	R/C Receiver	AG

Ref. No.	Part No.	★	Description	Code

CABINET PARTS LOCATION

1	CCABA2475CE01	J	Front Cabinet Ass'y	BE
1-1	*Not Available*	–	Front Cabinet	—
1-2	GCOVA1943CEKA	J	Button Cover(VOL)	AD
1-3	GCOVA1943CEKB	J	Button Cover(CH)	AD
1-4	GCOVA2098CEZZ	J	RC-LED Cover	AE
1-5	JBTN-2067CEKZ	J	Operation Button	AE
1-6	LANGT9057CEFW	J	Cabinet Fixing Angle	AE
1-7	PSPAG0417CEZZ	J	Spacer, x2	
1-8	PSPAG0418CEZZ	J	Spacer, x2	
1-9	PSPAGA020WJZZ	J	Spacer, x4	AB
1-10	PSPAGA022WJZZ	J	Spacer, x2	AB
1-11	PSPAH0676CEZZ	J	Spacer, x4	AA
1-12	PSPAH0678CEZZ	J	Spacer, x2	AA
1-13	PSPAH0728CEZZ	J	Spacer, x2	
1-14	PSPAH0729CEZZ	J	Spacer, x2	
1-15	PSPAH0730CEZZ	J	Light Shielding Spacer	
1-16	QCNW-A308WJZZ	J	Connecting Cord	AD
1-17	QEARZ0047CEZZ	J	Grounding Part	AC
1-18	VSP0050PBP68S	J	Speaker, x2	AT
1-19	XEBSD30P08000	J	Screw, x2	AA
1-20	XETSD40P08000	J	Screw, x8	AB
2	CCABB2360CE01	J	Rear Cabinet Ass'y	AZ
2-1	*Not Available*	–	Rear Cabinet	—
2-2	HiNDP5984CESA	J	Model Label	AG
2-3	LANGT9056CEFW	J	Fixing Metal	AN
2-4	PMLT-0409CEZZ	J	Light Shielding Spacer, x4	AC
2-5	PSPAG0433CEZZ	J	Spacer, x1	
2-6	PSPAH0731CEZZ	J	Spacer, x4	
2-7	XEBSD30P08000	J	Screw, x1	AA
3	CDAi-1120CE09	J	Stand Ass'y	BK
3-1	GDAi-1120CESA	J	Stand, Base	AX
3-2	GCOVA1945CESA	J	Stand Grip	AK
3-3	GDAi-1121CESA	J	Stand, Joint	AP
3-4	GLEGG9093CEZZ	J	Leg, x6	AC
3-5	JHNDP0103CESA	J	Stand Handle	AX
3-6	LANGG0114CEFW	J	Fixing Metal, x2	AE
3-7	LANGG1196CEFW	J	Fixing Metal	AF
3-8	LANGG1198CEFW	J	Fixing Metal	AE
3-9	LANGG1199CEFW	J	Fixing Metal	AD
3-10	LX-NZ3185CEFE	J	Nut	AC
3-11	MHNG-3044CEFW	J	Hinge(L)	AV
3-12	MHNG-3045CEFW	J	Hinge(R)	AP
3-13	MHNG-3051CEFW	J	Hinge(Side)	AV
3-14	PSPAT0079CEZZ	J	Spacer, x2	AC
3-15	PSPAZ0415CEZZ	J	Spacer, x2	AB
3-16	XESSD40P14000	J	Screw, x12	AB
3-17	XESSN40P10000	J	Screw, x8	AB
4	*Not Available*	–	15' LCD Panel Ass'y	—
4-1	RLCDTA003WJZZ	J	15' LCD Panel Unit	DB
⚠ 4-2	KLMP-0122CEZZ	J	Back Light Lamp	BD
4-3	PGiDM0070CEZZ	J	Light Guide Plate	BA
4-4	PMiR-0294CEZZ	J	Lamp Reflection Mirror	AG
4-5	PMiR-0295CEZZ	J	Lamp Reflection Mirror	AF
4-6	PSHEP0281CEZZ	J	Reflection/Deflection Sheet	BE
4-7	PSHEP0282CEZZ	J	Prism Sheet	AY
4-8	PSHEP0283CEZZ	J	Diffusion Sheet	AL
4-9	PSHEP0284CEZZ	J	Reflection Sheet-1	AG
4-10	PSHEP0285CEZZ	J	Reflection Sheet-2	AG
4-11	PSLDM4689CEFW	J	Shielding Plate	AR
4-12	QCNW-6064CEZZ	J	Source FFC	AD
4-13	QCNW-6065CEZZ	J	Connecting Cord	AC
4-14	QCNW-A069WJZZ	J	Gate FFC	AF
4-15	XBBSD30P05000	J	Screw, x4	AA
4-16	PSHEP0307CEZZ	J	Reflection Sheet (Cover)	AC
5	GCOVA2099CEKA	J	Terminal Cover(L)	AL
6	GCOVA2100CEKA	J	Terminal Cover(S)	AH
7	GCOVA2126CEKA	J	Chassis Frame	AP

CABINET AND MECHANICAL PARTS



CABINET PARTS LOCATION (Continued)

Ref. No.	Part No.	★	Description	Code
8	GCOVA2118CEKA	J	Chassis Frame Cover	AG
9	JBTN-2066CEKA	J	Power Button	AD
11	TLABN0452CEZZ	J	Serial No. Label (LC-15C2EA) (-Mar, 2002)	AE
11	TLABN0453CEZZ	J	Serial No. Label (LC-15C2EA(K)) (-Mar, 2002)	AE
11	TLABNA082WJZZ	J	Serial No. Label (LC-15C2EA) (Apr. 2002-)	
11	TLABNA084WJZZ	J	Serial No. Label (LC-15C2EA(K)) (Apr. 2002-)	
12	LANGK0782CEFW	J	Terminal Fixing Angle	AF
13	QCNW-A300WJZZ	J	Connecting Cord(MT)	AC
14	QCNW-A302WJZZ	J	Connecting Cord(MB)	AG
15	QCNW-A303WJZZ	J	Connecting Cord(VE/MS)	AH
16	QCNW-A385WJZZ	J	Connecting Cord(VE)	AE
17	QCNW-A386WJZZ	J	Connecting Cord(MA)	AD
18	LX-BZ3442CEFF	J	Screw, x4	AB
19	PSPAGA018WJZZ	J	Spacer, x3	AC
20	PSPAGA019WJZZ	J	Spacer	AB
21	PSPAGA021WJZZ	J	Spacer	AB
22	PSPAG2003CEZZ	J	Light Shielding Spacer	AA
23	PSPAHA009WJZZ	J	Light Shielding Spacer	AC
24	PSPAHA011WJZZ	J	Spacer	AB
25	XBBSF30P05000	J	Screw, x3	AB
26	XBPSN30P09JS0	J	Screw, x3	AB
27	XEBSD30P06000	J	Screw, x3	AA
28	XEBSD30P08000	J	Screw, x7	AA
29	XEBSD30P12000	J	Screw, x2	AA
30	XEBSF30P20000	J	Screw, x5	AB

ACCESSORIES

Ref. No.	Part No.	★	Description	Code
	LHLDW0109CESA	J	Cable Clamp, x2	AD
⚠	QACCK0006TAZZ	J	AC Cord(LC-15C2EA)	AL
⚠	QACCB0016TAZZ	J	AC Cord(LC-15C2EA(K))	AV
	RRMCGA031WJSA		Infrared RC Unit	AU
	TiNS-7626CEZZ	J	Operation Manual	BA
	TGAN-1688CEN1	J	Guarantee Card (LC-15C2EA(K))	AN
⚠	UADP-0240CEPZ	J	AC Adaptor	BK

PACKING PARTS
(NOT REPLACEMENT ITEM)

Part No.		Description	Code
SPAKC5693CEZZ	–	Packing Case	—
SPAKP0930CEZZ	–	Wrapping Paper	—
SPAKX2984CEZZ	–	Packing Material	—
SSAKA0160CEZZ	–	Polyethylene Bag	—
TLABK0001TAZZ	–	Label	—

PACKING OF THE SET



SHARP

COPYRIGHT © 2002 BY SHARP CORPORATION

ALL RIGHTS RESERVED.

No part of this publication may be reproduced,
stored in a retrieval system, or transmitted in
any form or by any means, electronic, mechanical,
photocopying, recording, or otherwise, without
prior written permission of the publisher.

ⒹJapan ⓅJapan TQ1293-S
Apr. 2002 Printed in Japan
NA. KG

SHARP CORPORATION
AV Systems Group
Quality & Reliability Control Center
Yaita, Tochigi 329-2193, Japan